



# TEST DATA OF LDA150W-12

(100V INPUT)

Regulated DC Power Supply

Dec. 1, 1999

Approved by : H. Yamaguchi  
Design Manager

Prepared by : T. Ashihara  
Design Engineer


**コーセル株式会社**  
**COSEL CO., LTD.**

## CONTENTS

1. Line Regulation	1
静的入力変動	
2. Input Current (by Load Current)	2
入力電流 (負荷特性)	
3. Input Power (by Load Current)	3
入力電力 (負荷特性)	
4. Efficiency (by Input Voltage)	4
効率 (入力電圧特性)	
5. Efficiency (by Load Current)	5
効率 (負荷特性)	
6. Hold-Up Time	6
出力保持時間	
7. Instantaneous Interruption Compensation	7
瞬時停電保障	
8. Load Regulation	8
静的負荷変動	
9. Ripple Voltage (by Load Current)	9
リップル電圧 (負荷特性)	
10. Ripple-Noise	10
リップルノイズ	
11. Overcurrent Protection	11
過電流保護	
12. Overvoltage Protection	12
過電圧保護	
13. Inrush Current	13
突入電流	
14. Dynamic Load Response	14
動的負荷変動	
15. Rise and Fall Time	15
立上り、立下り時間	
16. Ambient Temperature Drift	16
周囲温度変動	
17. Minimum Input Voltage for Regulated Output Voltage	17
最低レギュレーション電圧	
18. Ripple Voltage (by Ambient Temperature)	18
リップル電圧 (周囲温度特性)	
19. Time Lapse Drift	19
経時ドリフト	
20. Output Voltage Accuracy	20
定電圧精度	
21. Condensation	21
結露特性	
22. Leakage Current	22
漏洩電流	
23. Line Noise Tolerance	23
入力雑音耐量	
24. Conducted Emission	24
雑音端子電圧	
25. Figure of Testing Circuitry	25
測定回路図	

(Final Page 26 )


**COSEL**

Model LDA150W-12		Temperature 25°C Testing Circuitry Figure A																																
Item	Line Regulation 静的入力変動																																	
Object	+12.0V12.5A																																	
<p>1. Graph</p> <p>-----□----- Load 50%          -----△----- Load 100%</p> <p>[V]</p>  <p>Output Voltage [V]</p> <p>Input Voltage [V]</p> <p>Note: Slanted line shows the range of the rated input voltage.</p> <p>(注)斜線は定格入力電圧範囲を示す。</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Input Voltage [V]</th><th colspan="2">Output Voltage [V]</th></tr> <tr> <th>Load 50%</th><th>Load 100%</th></tr> </thead> <tbody> <tr><td>75</td><td>12.151</td><td>12.151</td></tr> <tr><td>80</td><td>12.151</td><td>12.151</td></tr> <tr><td>85</td><td>12.151</td><td>12.151</td></tr> <tr><td>90</td><td>12.151</td><td>12.151</td></tr> <tr><td>100</td><td>12.151</td><td>12.151</td></tr> <tr><td>110</td><td>12.151</td><td>12.151</td></tr> <tr><td>120</td><td>12.151</td><td>12.151</td></tr> <tr><td>132</td><td>12.151</td><td>12.151</td></tr> <tr><td>140</td><td>12.151</td><td>12.151</td></tr> </tbody> </table>	Input Voltage [V]	Output Voltage [V]		Load 50%	Load 100%	75	12.151	12.151	80	12.151	12.151	85	12.151	12.151	90	12.151	12.151	100	12.151	12.151	110	12.151	12.151	120	12.151	12.151	132	12.151	12.151	140	12.151	12.151
Input Voltage [V]	Output Voltage [V]																																	
	Load 50%	Load 100%																																
75	12.151	12.151																																
80	12.151	12.151																																
85	12.151	12.151																																
90	12.151	12.151																																
100	12.151	12.151																																
110	12.151	12.151																																
120	12.151	12.151																																
132	12.151	12.151																																
140	12.151	12.151																																

# COSEL

Model		LDA150W-12		Temperature		25℃																																																								
Item		Input Current (by Load Current) 入力電流 (負荷特性)		Testing Circuitry		Figure A																																																								
Output		_____																																																												
1. Graph				2. Values																																																										
<div><div>—△— Input Volt. 85V - - -□- - Input Volt. 100V - - -○- - Input Volt. 132V</div><div><div>[A]</div><div>5</div><div>4</div><div>3</div><div>2</div><div>1</div><div>0</div><div>0</div><div>5</div><div>10</div><div>15</div><div>Load Current</div><div>[A]</div></div></div> <table><tr><th rowspan="2">Load Current [A]</th><th colspan="3">Input Current [A]</th></tr><tr><th>Input Volt. 85[V]</th><th>Input Volt. 100[V]</th><th>Input Volt. 132[V]</th></tr><tr><td>0.00</td><td>0.156</td><td>0.172</td><td>0.176</td></tr><tr><td>2.00</td><td>0.792</td><td>0.732</td><td>0.642</td></tr><tr><td>4.00</td><td>1.320</td><td>1.191</td><td>1.012</td></tr><tr><td>6.00</td><td>1.853</td><td>1.657</td><td>1.385</td></tr><tr><td>8.00</td><td>2.404</td><td>2.136</td><td>1.767</td></tr><tr><td>10.00</td><td>2.938</td><td>2.600</td><td>2.137</td></tr><tr><td>12.00</td><td>3.492</td><td>3.073</td><td>2.517</td></tr><tr><td>12.50</td><td>3.640</td><td>3.198</td><td>2.614</td></tr><tr><td>13.75</td><td>3.987</td><td>3.490</td><td>2.847</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr></table> <div>Note: Slanted line shows the range of the rated load current</div> <div>(注)斜線は定格負荷電流範囲を示す。</div>				Load Current [A]	Input Current [A]			Input Volt. 85[V]	Input Volt. 100[V]	Input Volt. 132[V]	0.00	0.156	0.172	0.176	2.00	0.792	0.732	0.642	4.00	1.320	1.191	1.012	6.00	1.853	1.657	1.385	8.00	2.404	2.136	1.767	10.00	2.938	2.600	2.137	12.00	3.492	3.073	2.517	12.50	3.640	3.198	2.614	13.75	3.987	3.490	2.847	—	—	—	—	—	—	—	—	—	—	—	—				
Load Current [A]	Input Current [A]																																																													
	Input Volt. 85[V]	Input Volt. 100[V]	Input Volt. 132[V]																																																											
0.00	0.156	0.172	0.176																																																											
2.00	0.792	0.732	0.642																																																											
4.00	1.320	1.191	1.012																																																											
6.00	1.853	1.657	1.385																																																											
8.00	2.404	2.136	1.767																																																											
10.00	2.938	2.600	2.137																																																											
12.00	3.492	3.073	2.517																																																											
12.50	3.640	3.198	2.614																																																											
13.75	3.987	3.490	2.847																																																											
—	—	—	—																																																											
—	—	—	—																																																											
—	—	—	—																																																											

**COSEL**

Model		LDA150W-12		Temperature		25℃																																																								
Item		Input Power (by Load Current) 入力電力（負荷特性）		Testing Circuitry		Figure A																																																								
Output																																																														
1. Graph				2. Values																																																										
<div><div><div>△</div><div>□</div><div>○</div></div><div><div>Input Volt. 85V</div><div>Input Volt. 100V</div><div>Input Volt. 132V</div></div></div> <div><div><div><div>Input Power [W]</div><div>500</div><div>400</div><div>300</div><div>200</div><div>100</div><div>0</div></div><div><div>0</div><div>5</div><div>10</div><div>15</div></div><div><div>Load Current [A]</div></div></div></div> <div><div>Note: Slanted line shows the range of the rated load current</div><div>(注)斜線は定格負荷電流範囲を示す。</div></div>				<table><tr><th rowspan="2">Load Current [A]</th><th colspan="3">Input Power [W]</th></tr><tr><th>Input Volt. 85 [V]</th><th>Input Volt. 100 [V]</th><th>Input Volt. 132 [V]</th></tr><tr><td>0.00</td><td>3.12</td><td>4.01</td><td>5.86</td></tr><tr><td>2.00</td><td>32.42</td><td>33.47</td><td>36.00</td></tr><tr><td>4.00</td><td>60.58</td><td>61.20</td><td>63.30</td></tr><tr><td>6.00</td><td>89.40</td><td>89.60</td><td>91.20</td></tr><tr><td>8.00</td><td>119.40</td><td>119.10</td><td>119.90</td></tr><tr><td>10.00</td><td>149.40</td><td>148.30</td><td>148.40</td></tr><tr><td>12.00</td><td>181.10</td><td>179.10</td><td>178.30</td></tr><tr><td>12.50</td><td>189.20</td><td>186.90</td><td>185.80</td></tr><tr><td>13.75</td><td>209.40</td><td>206.40</td><td>204.50</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr></table>				Load Current [A]	Input Power [W]			Input Volt. 85 [V]	Input Volt. 100 [V]	Input Volt. 132 [V]	0.00	3.12	4.01	5.86	2.00	32.42	33.47	36.00	4.00	60.58	61.20	63.30	6.00	89.40	89.60	91.20	8.00	119.40	119.10	119.90	10.00	149.40	148.30	148.40	12.00	181.10	179.10	178.30	12.50	189.20	186.90	185.80	13.75	209.40	206.40	204.50	—	—	—	—	—	—	—	—	—	—	—	—
Load Current [A]	Input Power [W]																																																													
	Input Volt. 85 [V]	Input Volt. 100 [V]	Input Volt. 132 [V]																																																											
0.00	3.12	4.01	5.86																																																											
2.00	32.42	33.47	36.00																																																											
4.00	60.58	61.20	63.30																																																											
6.00	89.40	89.60	91.20																																																											
8.00	119.40	119.10	119.90																																																											
10.00	149.40	148.30	148.40																																																											
12.00	181.10	179.10	178.30																																																											
12.50	189.20	186.90	185.80																																																											
13.75	209.40	206.40	204.50																																																											
—	—	—	—																																																											
—	—	—	—																																																											
—	—	—	—																																																											

# COSEL

Model		LDA150W-12	
Item		Efficiency (by Input Voltage) 効率 (入力電圧特性)	
Object			

1. Graph

□

Load 50%

△

Load 100%

Efficiency [%]

86

82

78

74

70

66

62

0

0

80

90

100

110

120

130

140

150

Input Voltage [V]

80

90

100

110

120

130

140

150

Note: Slanted line shows the range of the rated input voltage.

(注)斜線は定格入力電圧範囲を示す。

Input Voltage [V]	Efficiency [%]	
	Load 50%	Load 100%
75	81.9	79.1
80	82.1	80.0
85	82.1	80.6
90	82.1	81.0
100	81.9	81.6
110	81.9	82.0
120	81.5	82.1
132	80.6	82.1
140	80.3	82.1

2. Values

# COSEL

Model		LDA150W-12	
Item		Efficiency (by Load Current) 効率 (負荷特性)	
Output		—	

1. Graph

—△— Input Volt. 85V

—□— Input Volt. 100V

—○— Input Volt. 132V

Efficiency [%]

Load Current [A]	85V [%]	100V [%]	132V [%]
2.00	76.1	74.1	69.0
4.00	80.9	80.1	77.6
6.00	81.8	81.8	80.4
8.00	81.9	82.1	81.8
10.00	81.4	82.1	82.1
12.00	80.7	81.7	82.1
12.50	80.5	81.6	82.1
13.75	80.0	81.2	81.9
—	—	—	—
—	—	—	—
—	—	—	—
—	—	—	—

Load Current [A]

Note: Slanted line shows the range of the rated load current

(注)斜線は定格負荷電流範囲を示す。

2. Values

Load Current [A]	Efficiency [%]		
	Input Volt. 85[V]	Input Volt. 100[V]	Input Volt. 132[V]
2.00	76.1	74.1	69.0
4.00	80.9	80.1	77.6
6.00	81.8	81.8	80.4
8.00	81.9	82.1	81.8
10.00	81.4	82.1	82.1
12.00	80.7	81.7	82.1
12.50	80.5	81.6	82.1
13.75	80.0	81.2	81.9
—	—	—	—
—	—	—	—
—	—	—	—
—	—	—	—


Model LDA150W-12		Temperature 25°C Testing Circuitry Figure A																																
Item	Hold-Up Time 出力保持時間																																	
Object	+12.0V 12.5A																																	
<p>1. Graph</p> <p>-----□----- Load 50%          -----△----- Load 100%</p> <p>[mS]</p> <p>Hold-Up Time</p> <p>Input Voltage [V]</p>		2. Values																																
<p>This duration covers from Shut-off of input voltage to the moment when output voltage descends to the rated range of voltage accuracy.</p> <p>Note: Slanted line shows the range of the rated input voltage.</p> <p>出力保持時間とは、入力電圧断から出力電圧が、定電圧精度の規格範囲を保持しているところまでの時間。</p> <p>(注) 斜線は定格入力電圧範囲を示す。</p>		<table> <tr> <th rowspan="2">Input Voltage [V]</th><th colspan="2">Hold-Up Time [mS]</th></tr> <tr> <th>Load 50%</th><th>Load 100%</th></tr> <tr><td>75</td><td>28</td><td>9</td></tr> <tr><td>80</td><td>35</td><td>12</td></tr> <tr><td>85</td><td>43</td><td>16</td></tr> <tr><td>90</td><td>51</td><td>20</td></tr> <tr><td>100</td><td>68</td><td>29</td></tr> <tr><td>110</td><td>87</td><td>38</td></tr> <tr><td>120</td><td>108</td><td>48</td></tr> <tr><td>132</td><td>136</td><td>62</td></tr> <tr><td>140</td><td>155</td><td>72</td></tr> </table>	Input Voltage [V]	Hold-Up Time [mS]		Load 50%	Load 100%	75	28	9	80	35	12	85	43	16	90	51	20	100	68	29	110	87	38	120	108	48	132	136	62	140	155	72
Input Voltage [V]	Hold-Up Time [mS]																																	
	Load 50%	Load 100%																																
75	28	9																																
80	35	12																																
85	43	16																																
90	51	20																																
100	68	29																																
110	87	38																																
120	108	48																																
132	136	62																																
140	155	72																																



# COSEL

Model		LDA150W-12		Temperature		25°C																																																				
Item		Instantaneous Interruption Compensation 瞬時停電保障		Testing Circuitry		Figure A																																																				
Object		+12.0V12.5A																																																								
1. Graph				2. Values																																																						
<div><div><div>—△—</div><div>—□—</div><div>—○—</div></div><div>Input Volt. 85 V</div><div>Input Volt.100 V</div><div>Input Volt.132 V</div></div> <div><div>[mS]</div><div>1000</div><div>100</div><div>10</div><div>1</div><div>Instantaneous Compensation Time</div><div>0</div><div>5</div><div>10</div><div>15</div><div>Load Current</div><div>[A]</div></div> <div><div>This duration covers from Shut-off of input voltage to the moment when output voltage descends to the rated range of voltage accuracy.</div><div>Note:Slanted line shows the range of the rated load current.</div></div>				<table><tr><th rowspan="2">Load Current [A]</th><th colspan="3">Time [mS]</th></tr><tr><th>Input Volt. 85[V]</th><th>Input Volt. 100[V]</th><th>Input Volt. 132[V]</th></tr><tr><td>0.00</td><td>—</td><td>—</td><td>—</td></tr><tr><td>2.00</td><td>132</td><td>205</td><td>397</td></tr><tr><td>4.00</td><td>58</td><td>104</td><td>206</td></tr><tr><td>6.00</td><td>34</td><td>65</td><td>138</td></tr><tr><td>8.00</td><td>26</td><td>42</td><td>103</td></tr><tr><td>10.00</td><td>17</td><td>33</td><td>79</td></tr><tr><td>12.00</td><td>10</td><td>26</td><td>63</td></tr><tr><td>12.50</td><td>10</td><td>25</td><td>61</td></tr><tr><td>13.75</td><td>10</td><td>17</td><td>54</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr></table>				Load Current [A]	Time [mS]			Input Volt. 85[V]	Input Volt. 100[V]	Input Volt. 132[V]	0.00	—	—	—	2.00	132	205	397	4.00	58	104	206	6.00	34	65	138	8.00	26	42	103	10.00	17	33	79	12.00	10	26	63	12.50	10	25	61	13.75	10	17	54	—	—	—	—	—	—	—	—
Load Current [A]	Time [mS]																																																									
	Input Volt. 85[V]	Input Volt. 100[V]	Input Volt. 132[V]																																																							
0.00	—	—	—																																																							
2.00	132	205	397																																																							
4.00	58	104	206																																																							
6.00	34	65	138																																																							
8.00	26	42	103																																																							
10.00	17	33	79																																																							
12.00	10	26	63																																																							
12.50	10	25	61																																																							
13.75	10	17	54																																																							
—	—	—	—																																																							
—	—	—	—																																																							
<div>瞬時停電保障時間とは、出力電圧が定電圧精度の規格範囲を保持している瞬時停電時間をいう。</div> <div>(注)斜線は定格負荷電流範囲を示す。</div>																																																										

**COSEL**

Model		LDA150W-12		Temperature		25℃																																																
Item		Load Regulation 静的負荷変動		Testing Circuitry		Figure A																																																
Object		+12.0V12.5A																																																				
1. Graph				2. Values																																																		
<div><div><div>△</div><div>—</div><div>Input Volt. 85 V</div></div><div><div>□</div><div>- - -</div><div>Input Volt. 100 V</div></div><div><div>○</div><div>⋯</div><div>Input Volt. 132 V</div></div></div> <div><div><div>Output Voltage [V]</div><div><div>12.290</div><div>12.250</div><div>12.210</div><div>12.170</div><div>12.130</div><div>12.090</div><div>12.050</div><div>0</div></div><div><div>0</div><div>5</div><div>10</div><div>15</div></div><div>Load Current [A]</div></div></div> <div><div>Note: Slanted line shows the range of the rated load current.</div><div>(注)斜線は定格負荷電流範囲を示す。</div></div>				<table><tr><th rowspan="2">Load Current [A]</th><th colspan="3">Output Voltage [V]</th></tr><tr><th>Input Volt. 85[V]</th><th>Input Volt. 100[V]</th><th>Input Volt. 132[V]</th></tr><tr><td>0.00</td><td>12.151</td><td>12.151</td><td>12.151</td></tr><tr><td>2.00</td><td>12.150</td><td>12.150</td><td>12.150</td></tr><tr><td>4.00</td><td>12.150</td><td>12.150</td><td>12.151</td></tr><tr><td>6.00</td><td>12.151</td><td>12.151</td><td>12.151</td></tr><tr><td>8.00</td><td>12.151</td><td>12.151</td><td>12.151</td></tr><tr><td>10.00</td><td>12.151</td><td>12.151</td><td>12.151</td></tr><tr><td>12.00</td><td>12.151</td><td>12.151</td><td>12.151</td></tr><tr><td>12.50</td><td>12.151</td><td>12.151</td><td>12.151</td></tr><tr><td>13.75</td><td>12.151</td><td>12.151</td><td>12.151</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr></table>				Load Current [A]	Output Voltage [V]			Input Volt. 85[V]	Input Volt. 100[V]	Input Volt. 132[V]	0.00	12.151	12.151	12.151	2.00	12.150	12.150	12.150	4.00	12.150	12.150	12.151	6.00	12.151	12.151	12.151	8.00	12.151	12.151	12.151	10.00	12.151	12.151	12.151	12.00	12.151	12.151	12.151	12.50	12.151	12.151	12.151	13.75	12.151	12.151	12.151	—	—	—	—
Load Current [A]	Output Voltage [V]																																																					
	Input Volt. 85[V]	Input Volt. 100[V]	Input Volt. 132[V]																																																			
0.00	12.151	12.151	12.151																																																			
2.00	12.150	12.150	12.150																																																			
4.00	12.150	12.150	12.151																																																			
6.00	12.151	12.151	12.151																																																			
8.00	12.151	12.151	12.151																																																			
10.00	12.151	12.151	12.151																																																			
12.00	12.151	12.151	12.151																																																			
12.50	12.151	12.151	12.151																																																			
13.75	12.151	12.151	12.151																																																			
—	—	—	—																																																			

# COSEL

Model		LDA150W-12	
Item		Ripple Voltage (by Load Current) リップル電圧 (負荷電流特性)	
Object		+12.0V 12.5A	

1. Graph

□

Input Volt. 85V

△

Input Volt. 132V

Ripple Voltage [mV]

150

125

100

75

50

25

0

0

5

10

15

Load Current [A]

Ripple Voltage is shown as p-p in the figure below.

Note: Slanted line shows the range of the rated load current.

リップル電圧は、下図 p - p 値で示される。

(注)斜線は定格負荷電流範囲を示す。

T1: Due to AC Input Line  
入力商用周期

T2: Due to Switching  
スイッチング周期

Ripple [mVp-p]

T2


T1

Fig. Complex Ripple Wave Form

図 リップル波形詳細図

2. Values

Load Current [A]	Input Volt. 85 [V]	Input Volt. 132 [V]
	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]
0.00	10	10
2.00	15	20
4.00	20	20
6.00	20	25
8.00	25	25
10.00	30	30
12.00	35	30
12.50	40	30
13.80	45	30
—	—	—
—	—	—

**COSEL**

**COSEL**

Model		LDA150W-12	Temperature		25℃
Item		Overcurrent Protection 過電流保護	Testing Circuitry		Figure A
Object		+12.0V 12.5A			
1. Graph			2. Values		

Input Volt. 85 V  
Input Volt. 100 V  
Input Volt. 132 V

[V]

20.0

15.0

10.0

5.0

0.0

Output Voltage

0

5

10

15

20

Load Current

[A]

Note: Slanted line shows the range of the rated load current.

(注) 斜線は定格負荷電流範囲を示す。

Output Voltage [V]	Load Current [A]		
	Input Volt. 85 [V]	Input Volt. 100 [V]	Input Volt. 132 [V]
12.00	15.176	15.111	15.137
11.40	15.210	15.153	15.186
10.80	15.242	15.193	15.294
9.60	15.309	15.283	15.327
8.40	15.414	15.364	15.428
7.20	15.455	15.460	15.533
6.00	15.531	15.536	15.583
4.80	15.591	15.591	15.636
3.60	15.636	15.629	15.694
2.40	15.700	15.652	15.599
1.20	15.427	15.309	15.088
0.00	14.900	14.872	14.767

# COSEL

Model	LDA150W-12
Item	Overvoltage Protection 過電圧保護
Object	+12.0V 12.5A
<p>1. Graph</p> <p> <span style="display: inline-block; width: 20px; border-bottom: 1px solid black; margin-right: 5px;"></span>△ Input Volt. 85 V  <span style="display: inline-block; width: 20px; border-bottom: 1px dashed black; margin-right: 5px;"></span>□ Input Volt. 100 V  <span style="display: inline-block; width: 20px; border-bottom: 1px dotted black; margin-right: 5px;"></span>○ Input Volt. 132 V </p> <p>[V]</p> <p>Operating Point</p> <p>Ambient Temperature [°C]</p> <p>Load 0%</p> <p>Note: Slanted line shows the range of the rated ambient temperature.</p> <p>(注) 斜線は定格周囲温度範囲を示す。</p>	


Testing Circuitry Figure A

## 2. Values


Ambient Temperature [°C]	Operating Point [V]		
	Input Volt. 85[V]	Input Volt. 100[V]	Input Volt. 132[V]
-20	15.04	15.04	15.04
-10	15.16	15.16	15.16
0	15.22	15.22	15.22
10	15.33	15.34	15.34
20	15.46	15.46	15.46
25	15.46	15.46	15.46
30	15.52	15.52	15.52
40	15.64	15.64	15.64
50	15.70	15.70	15.70
60	15.82	15.82	15.82
—	—	—	—

**COSEL**

Model	LDA150W-12	Temperature	25°C
Item	Inrush Current 突入電流	Testing Circuitry	Figure A
Object			



Input Voltage 100 V  
 Frequency 60 Hz  
 Load 100 %  
 Inrush Current  
 ① 13.20 [A]  
 ② 8.40 [A]



**COSEL**

Model	LDA150W-12		
Item	Dynamic Load Responce 動的負荷変動	Temperature	25℃
Object	+12.0V12.5A	Testing Circuitry	Figure A

Input Volt. 100 V



Cycle 1000 mS

Load Current





Load 0% ↔

Load 100 %



Load 0% ↔

Load 50 %




100 mV/div

10 mS/div



# COSEL



# COSEL

Model		LDA150W-12		Testing Circuitry	Figure A																																																			
Item		Ambient Temperature Drift 周囲温度変動																																																						
Object		+12.0V 12.5A																																																						
1. Graph		<div><div>△</div> Input Volt. 85V</div> <div><div>□</div> Input Volt. 100V</div> <div><div>○</div> Input Volt. 132V</div> <p>Output Voltage [V]</p> <p>Ambient Temperature [°C]</p> <p>Load 100%</p>		2. Values																																																				
		<table><tr><th rowspan="2">Ambient Temperature [°C]</th><th colspan="3">Output Voltage [V]</th></tr><tr><th>Input Volt. 85 [V]</th><th>Input Volt. 100 [V]</th><th>Input Volt. 132 [V]</th></tr><tr><td>-20</td><td>12.170</td><td>12.170</td><td>12.170</td></tr><tr><td>-10</td><td>12.166</td><td>12.166</td><td>12.166</td></tr><tr><td>0</td><td>12.161</td><td>12.161</td><td>12.161</td></tr><tr><td>10</td><td>12.157</td><td>12.157</td><td>12.157</td></tr><tr><td>20</td><td>12.153</td><td>12.153</td><td>12.154</td></tr><tr><td>25</td><td>12.152</td><td>12.152</td><td>12.152</td></tr><tr><td>30</td><td>12.151</td><td>12.151</td><td>12.151</td></tr><tr><td>40</td><td>12.144</td><td>12.145</td><td>12.145</td></tr><tr><td>50</td><td>12.137</td><td>12.137</td><td>12.137</td></tr><tr><td>60</td><td>12.127</td><td>12.127</td><td>12.127</td></tr><tr><td>—</td><td>—</td><td>—</td><td>—</td></tr></table>		Ambient Temperature [°C]	Output Voltage [V]			Input Volt. 85 [V]	Input Volt. 100 [V]	Input Volt. 132 [V]	-20	12.170	12.170	12.170	-10	12.166	12.166	12.166	0	12.161	12.161	12.161	10	12.157	12.157	12.157	20	12.153	12.153	12.154	25	12.152	12.152	12.152	30	12.151	12.151	12.151	40	12.144	12.145	12.145	50	12.137	12.137	12.137	60	12.127	12.127	12.127	—	—	—	—		
Ambient Temperature [°C]	Output Voltage [V]																																																							
	Input Volt. 85 [V]	Input Volt. 100 [V]	Input Volt. 132 [V]																																																					
-20	12.170	12.170	12.170																																																					
-10	12.166	12.166	12.166																																																					
0	12.161	12.161	12.161																																																					
10	12.157	12.157	12.157																																																					
20	12.153	12.153	12.154																																																					
25	12.152	12.152	12.152																																																					
30	12.151	12.151	12.151																																																					
40	12.144	12.145	12.145																																																					
50	12.137	12.137	12.137																																																					
60	12.127	12.127	12.127																																																					
—	—	—	—																																																					
Note: Slanted line shows the range of the rated ambient temperature.																																																								
(注)斜線は定格周囲温度範囲を示す。																																																								

# COSEL

Model		LDA150W-12	
Item		Minimum Input Voltage for Regulated Output Voltage 最低レギュレーション電圧	
Object		+12.0V12.5A	

1. Graph

□

Load 50%

△

Load 100%

Input Voltage [V]

100.0

80.0

60.0

40.0

20.0

0.0

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—

—


—

**COSEL**

Model	LDA150W-12
Item	Ripple Voltage (by Ambient Temp.) リップル電圧 (周囲温度特性)
Object	+12.0V12.5A

Testing Circuitry      Figure A

## 1. Graph



Note: Slanted line shows the range of the rated ambient temperature.

(注) 斜線は定格周囲温度範囲を示す。

## 2. Values

Ambient Temp. [°C]	Load 50%	Load 100%
	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]
-20	45	60
-10	35	50
0	35	45
10	30	40
20	30	40
25	25	40
30	25	40
40	25	35
50	25	35
60	25	35
—	—	—

**COSEL**

COSEL																									
Model	LDA150W-12	Temperature 25℃ Testing Circuitry Figure A																							
Item	Time Lapse Drift 経時ドリフト																								
Object	+12.0V12.5A																								
1. Graph		2.Values																							
<div><div>[V]</div><div><div>Output Voltage</div><div>Time</div></div><div><div>Input Volt.</div><div>100V</div><div>Load</div><div>100%</div></div></div>		<table><tr><th>Time since start [H]</th><th>Output Voltage [V]</th></tr><tr><td>0.0</td><td>12.154</td></tr><tr><td>0.5</td><td>12.146</td></tr><tr><td>1.0</td><td>12.146</td></tr><tr><td>2.0</td><td>12.146</td></tr><tr><td>3.0</td><td>12.146</td></tr><tr><td>4.0</td><td>12.146</td></tr><tr><td>5.0</td><td>12.146</td></tr><tr><td>6.0</td><td>12.146</td></tr><tr><td>7.0</td><td>12.146</td></tr><tr><td>8.0</td><td>12.146</td></tr></table>		Time since start [H]	Output Voltage [V]	0.0	12.154	0.5	12.146	1.0	12.146	2.0	12.146	3.0	12.146	4.0	12.146	5.0	12.146	6.0	12.146	7.0	12.146	8.0	12.146
Time since start [H]	Output Voltage [V]																								
0.0	12.154																								
0.5	12.146																								
1.0	12.146																								
2.0	12.146																								
3.0	12.146																								
4.0	12.146																								
5.0	12.146																								
6.0	12.146																								
7.0	12.146																								
8.0	12.146																								

Model		LDA150W-12	Testing Circuitry    Figure A
Item		Output Voltage Accuracy    定電圧精度	
Object		+12.0V 12.5A	

### 1. Output Voltage Accuracy

This is defined as the value of the output voltage, regulation load, ambient temperature and input voltage varied at random in the range as specified below.

Temperature    -10~50 °C

Input Voltage :    85~132 V

Load Current :    0~12.5 A

\* Output Voltage Accuracy =  $\pm (\text{Maximum of Output Voltage} - \text{Minimum of Output Voltage}) / 2$

\* Output Voltage Accuracy (Ration) =  $\frac{\text{Output Voltage Accuracy}}{\text{Rated Output Voltage}} \times 100$

### 1. 定電圧精度

周囲温度、入力電圧、負荷電流を下記仕様内で、任意に変動させたときの出力電圧の変動をいう。

周囲温度            -10~50 °C

入力電圧            85~132 V

負荷電流            0~12.5 A

\* 定電圧精度(変動値) =  $\pm (\text{出力電圧の最高値} - \text{出力電圧の最低値}) / 2$

\* 定電圧精度(変動率) =  $\frac{\text{変動値}}{\text{定格出力電圧}} \times 100$

### 2. Values

Item	Temperature [°C]	Input Voltage [V]	Output Current [A]	Output Voltage [V]	Output Voltage Accuracy [mV]	Output Voltage Accuracy(Ration) [%]
Maximum Voltage	-10	132	0.0	12.166	±16	±0.2
Minimum Voltage	50	132	12.5	12.135		



Model		LDA150W-12	Temperature Testing Circuitry	25°C Figure B
Item		Leakage Current 漏洩電流		
Object		_____		

## 1. Results

Standards	Leakage Current [mA]		
	Input Volt. 85 [V]	Input Volt. 100 [V]	Input Volt. 132 [V]
(A) DENTORI	0.17	0.20	0.25
(B) IEC60950	0.17	0.20	0.25

Standards	Leakage Current [mA]		
	Input Volt. 170 [V]	Input Volt. 230 [V]	Input Volt. 264 [V]
(B) IEC60950	—	—	—

## 2. Condition

Leakage current value is concluded after measuring both phases of AC input and by choosing the larger one.

交流入力 of 両相について測定し、その大きい方を漏洩電流測定値とする。



# COSEL

Model		LDA150F-12	Temperature 25°C Testing Circuitry Figure C
Item		Line Noise Tolerance 入力雑音耐量	
Object		+12.0V 12.5A	

## 1. Results

Pulse Width [ nS ]	MODE	No protection failure should occur 保護回路の誤動作がない	DC-like Regulation of Output Voltage 出力電圧の直流的変動
50	COMMON	OK	no fluctuation
	NORMAL	OK	no fluctuation
1000	COMMON	OK	no fluctuation
	NORMAL	OK	no fluctuation

## 2. Conditions

Input Voltage : 100 V  
 Pulse Voltage : 2000 V  
 Pulse Cycle : 10 mS  
 Pulse Input Duration : 1 min. or more  
 Load : 100 %

**COSEL**

Model	LDA150W-12	Temperature	25°C
Item	Conducted Emission 雑音端子電圧	Testing Circuitry	Figure D
Object			

## 1. Graph

## Remarks


Input Volt. 100 V (VCCI Class B)

120 V (FCC Class B)


Load 100 %

規格1: [VCCI] Class B(平均値)

規格2: [VCCI] Class B(QP)



規格1: [FCC Part15] Class B



**COSEL**





Figure B (DENTORI)




Figure B (IEC 60950)




Figure C




Figure D




Figure E