



EMI/EMS Test Result

According to IEC60601-1-2 4th Edition (EMS)

Model Name : PJMA1000F series

Approved : Takashi Kajii

The EUT is operated with following condition during EMI/EMS test.

Input Voltage : 115,230VAC / 50,60Hz
 Output Current : Rated Current
 Ambient Temperature : 25°C ± 10°C

Prepared : Akihisa Mukai

#	Subject	Reference standard	Test Condition	Criteria *1	Result		
1	EMI		Conducted Emission	EN55011, EN55032 Class B CISPR 32 Class B FCC Part15 Class B VCCI Class B	-	Pass	
			Radiated Emission	EN55011, EN55032 Class B CISPR 32 Class B FCC Part15 Class B VCCI Class B	-	Pass	
			Harmonic Current	IEC61000-3-2	Class A	-	Pass
4	EMS	IEC61000-4-2	Electrostatic discharge immunity test	Contact Discharge : Level 4 (8kV) Air Discharge : Level 4 (15kV)	A	Pass	
5			Radiated, radio-frequency, electromagnetic field immunity test	10V/m : (80MHz~2.7GHz) 80% Amplitude modulated	A	Pass	
6			Electrical fast transient / Burst immunity test	IEC61000-4-4	Level 4 (4kV) Repetition Rate : 5kHz and 100kHz	A	Pass
7			Surge immunity test	IEC61000-4-5	Line to Line : Level 4 (2kV) Line to Earth : Level 4 (4kV)	B	Pass
8			Immunity to conducted disturbances, induced by radio-frequency fields	IEC61000-4-6	Voltage Level (e.m.f.) : Level 3 (10Vrms)	A	Pass
9			Power frequency magnetic field Immunity test	IEC61000-4-8	Magnetic Field Strength : Level 4 (30A/m)	A	Pass
10			Voltage dips, short interruptions and voltage variations immunity test	IEC61000-4-11	(1) 100% dip for 10ms, 0°, 45°, 90°, 135°, 180°, 225°, 270° and 315°	A	Pass
	(2) 100% dip for 20ms, 0°	A			*2 Pass		
			(3) 30% dip for 500ms, 0°	A	*3 Pass		
			(4) 100% dip for 5 seconds (short interruption)	B	Pass		

*1 Definition of Criteria

Criteria A : (1) No output voltage drop with control circuit failure.
 (2) No protection circuit and other circuit malfunction.

Criteria B : (1) The output voltage is temporary degradation of performance.
 It recovers its normal performance without operator intervention.
 (2) No protection circuit and other circuit failure.

*2 Output Current:10% or less of rated current(at 100VAC)

*3 Output Current:70% or less of rated current(at 100VAC)

<Notes>

Power supply shall not determine the final equipment performance against EMS test. Therefore we confirmed the output voltage performance only. EMS test should be performed as a final product.