



# TEST DATA OF SFS204805

Regulated DC Power Supply  
Sep 6, 2004

Approved by : Isao Yasuda  
Isao Yasuda Design Manager

Prepared by : Kazuhiko Horii  
Kazuhiko Horii Design Engineer

COSEL CO.,LTD.

## CONTENTS

1. Input Current (by Input Voltage) . . . . .	1
2. Input Current (by Load Current) . . . . .	2
3. Input Power (by Load Current) . . . . .	3
4. Efficiency (by Input Voltage) . . . . .	4
5. Efficiency (by Load Current) . . . . .	5
6. Line Regulation . . . . .	6
7. Load Regulation . . . . .	7
8. Dynamic Load Response . . . . .	8
9. Ripple Voltage (by Load Current) . . . . .	9
10. Ripple-Noise . . . . .	10
11. Ripple Voltage (by Ambient Temperature) . . . . .	11
12. Ambient Temperature Drift . . . . .	12
13. Output Voltage Accuracy . . . . .	13
14. Time Lapse Drift . . . . .	14
15. Rise and Fall Time . . . . .	15
16. Minimum Input Voltage for Regulated Output Voltage . . . . .	16
17. Overcurrent Protection . . . . .	17
18. Overvoltage Protection . . . . .	18
19. Figure of Testing Circuitry . . . . .	19

(Final Page 19)

**COSSEL**

Model	SFS204805	Temperature 25°C Testing Circuitry Figure A																																																																									
Item	Input Current (by Input Voltage)																																																																										
Object	_____																																																																										
1.Graph	_____																																																																										
	<p>The graph plots Input Current [A] on the y-axis (0.0 to 1.0) against Input Voltage [V] on the x-axis (0 to 80). Three data series are shown: Load 100% (triangles), Load 50% (squares), and Load 0% (circles). A slanted line indicates the rated input voltage range.</p> <table border="1"> <thead> <tr> <th>Input Voltage [V]</th> <th>Load 100% [A]</th> <th>Load 50% [A]</th> <th>Load 0% [A]</th> </tr> </thead> <tbody> <tr><td>0</td><td>0.000</td><td>0.000</td><td>0.000</td></tr> <tr><td>8</td><td>0.001</td><td>0.001</td><td>0.001</td></tr> <tr><td>16</td><td>0.001</td><td>0.001</td><td>0.001</td></tr> <tr><td>24</td><td>0.002</td><td>0.002</td><td>0.002</td></tr> <tr><td>33</td><td>0.002</td><td>0.002</td><td>0.002</td></tr> <tr><td>34</td><td>0.030</td><td>0.330</td><td>0.639</td></tr> <tr><td>36</td><td>0.027</td><td>0.313</td><td>0.618</td></tr> <tr><td>40</td><td>0.023</td><td>0.280</td><td>0.546</td></tr> <tr><td>48</td><td>0.021</td><td>0.236</td><td>0.461</td></tr> <tr><td>60</td><td>0.020</td><td>0.192</td><td>0.367</td></tr> <tr><td>70</td><td>0.019</td><td>0.167</td><td>0.317</td></tr> <tr><td>76</td><td>0.019</td><td>0.156</td><td>0.296</td></tr> <tr><td>80</td><td>0.019</td><td>0.149</td><td>0.279</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	Input Voltage [V]	Load 100% [A]	Load 50% [A]	Load 0% [A]	0	0.000	0.000	0.000	8	0.001	0.001	0.001	16	0.001	0.001	0.001	24	0.002	0.002	0.002	33	0.002	0.002	0.002	34	0.030	0.330	0.639	36	0.027	0.313	0.618	40	0.023	0.280	0.546	48	0.021	0.236	0.461	60	0.020	0.192	0.367	70	0.019	0.167	0.317	76	0.019	0.156	0.296	80	0.019	0.149	0.279	--	-	-	-	--	-	-	-	--	-	-	-						
Input Voltage [V]	Load 100% [A]	Load 50% [A]	Load 0% [A]																																																																								
0	0.000	0.000	0.000																																																																								
8	0.001	0.001	0.001																																																																								
16	0.001	0.001	0.001																																																																								
24	0.002	0.002	0.002																																																																								
33	0.002	0.002	0.002																																																																								
34	0.030	0.330	0.639																																																																								
36	0.027	0.313	0.618																																																																								
40	0.023	0.280	0.546																																																																								
48	0.021	0.236	0.461																																																																								
60	0.020	0.192	0.367																																																																								
70	0.019	0.167	0.317																																																																								
76	0.019	0.156	0.296																																																																								
80	0.019	0.149	0.279																																																																								
--	-	-	-																																																																								
--	-	-	-																																																																								
--	-	-	-																																																																								
2.Values																																																																											
	<table border="1"> <thead> <tr> <th rowspan="2">Input Voltage [V]</th> <th colspan="3">Input Current [A]</th> </tr> <tr> <th>Load 0%</th> <th>Load 50%</th> <th>Load 100%</th> </tr> </thead> <tbody> <tr><td>0</td><td>0.000</td><td>0.000</td><td>0.000</td></tr> <tr><td>8</td><td>0.001</td><td>0.001</td><td>0.001</td></tr> <tr><td>16</td><td>0.001</td><td>0.001</td><td>0.001</td></tr> <tr><td>24</td><td>0.002</td><td>0.002</td><td>0.002</td></tr> <tr><td>33</td><td>0.002</td><td>0.002</td><td>0.002</td></tr> <tr><td>34</td><td>0.030</td><td>0.330</td><td>0.639</td></tr> <tr><td>36</td><td>0.027</td><td>0.313</td><td>0.618</td></tr> <tr><td>40</td><td>0.023</td><td>0.280</td><td>0.546</td></tr> <tr><td>48</td><td>0.021</td><td>0.236</td><td>0.461</td></tr> <tr><td>60</td><td>0.020</td><td>0.192</td><td>0.367</td></tr> <tr><td>70</td><td>0.019</td><td>0.167</td><td>0.317</td></tr> <tr><td>76</td><td>0.019</td><td>0.156</td><td>0.296</td></tr> <tr><td>80</td><td>0.019</td><td>0.149</td><td>0.279</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	Input Voltage [V]	Input Current [A]			Load 0%	Load 50%	Load 100%	0	0.000	0.000	0.000	8	0.001	0.001	0.001	16	0.001	0.001	0.001	24	0.002	0.002	0.002	33	0.002	0.002	0.002	34	0.030	0.330	0.639	36	0.027	0.313	0.618	40	0.023	0.280	0.546	48	0.021	0.236	0.461	60	0.020	0.192	0.367	70	0.019	0.167	0.317	76	0.019	0.156	0.296	80	0.019	0.149	0.279	--	-	-	-	--	-	-	-	--	-	-	-			
Input Voltage [V]	Input Current [A]																																																																										
	Load 0%	Load 50%	Load 100%																																																																								
0	0.000	0.000	0.000																																																																								
8	0.001	0.001	0.001																																																																								
16	0.001	0.001	0.001																																																																								
24	0.002	0.002	0.002																																																																								
33	0.002	0.002	0.002																																																																								
34	0.030	0.330	0.639																																																																								
36	0.027	0.313	0.618																																																																								
40	0.023	0.280	0.546																																																																								
48	0.021	0.236	0.461																																																																								
60	0.020	0.192	0.367																																																																								
70	0.019	0.167	0.317																																																																								
76	0.019	0.156	0.296																																																																								
80	0.019	0.149	0.279																																																																								
--	-	-	-																																																																								
--	-	-	-																																																																								
--	-	-	-																																																																								

Note: Slanted line shows the range of the rated input voltage.

COSEL


Model SFS204805

Item Input Current (by Load Current)

Object \_\_\_\_\_

1.Graph

—△— Input Volt. 36V  
 - -□--- Input Volt. 48V  
 - -○--- Input Volt. 76V



Note: Slanted line shows the range of the rated load current.

Temperature 25°C  
 Testing Circuitry Figure A

2.Values

Load Current [A]	Input Current [A]		
	Input Volt. 36[V]	Input Volt. 48[V]	Input Volt. 76[V]
0.0	0.027	0.020	0.019
0.8	0.140	0.106	0.073
1.6	0.256	0.193	0.128
2.4	0.374	0.281	0.184
3.2	0.495	0.370	0.240
4.0	0.618	0.461	0.296
4.4	0.681	0.506	0.324
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-

**COSEL**


Model SFS204805

Item Input Power (by Load Current)

Object \_\_\_\_\_

1.Graph

—△— Input Volt. 36V  
 - -□--- Input Volt. 48V  
 - -○--- Input Volt. 76V



Note: Slanted line shows the range of the rated load current.

 Temperature 25°C  
 Testing Circuitry Figure A

2.Values

Load Current [A]	Input Power [W]		
	Input Volt. 36[V]	Input Volt. 48[V]	Input Volt. 76[V]
0.0	1.00	1.01	1.53
0.8	5.10	5.14	5.64
1.6	9.26	9.31	9.84
2.4	13.50	13.54	14.04
3.2	17.86	17.81	18.30
4.0	22.22	22.19	22.56
4.4	24.46	24.38	24.72
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-


**COSEL**

Model SFS204805

Item Efficiency (by Input Voltage)

Object

## 1. Graph



Note: Slanted line shows the range of the rated input voltage.

 Temperature 25°C  
 Testing Circuitry Figure A

## 2. Values


Input Voltage [V]	Efficiency [%]	
	Load 50%	Load 100%
34	87.5	88.8
36	88.3	89.6
40	89.0	90.0
48	88.3	90.0
55	87.5	89.9
60	86.9	89.6
70	85.2	88.7
76	84.3	88.3
78	84.2	88.1

**COSEL**

Model SFS204805

Item Efficiency (by Load Current)

Object \_\_\_\_\_

Temperature 25°C  
Testing Circuitry Figure A


## 2.Values

Load Current [A]	Efficiency [%]		
	Input Volt. 36[V]	Input Volt. 48[V]	Input Volt. 76[V]
0.0	-	-	-
0.8	79.4	78.9	71.9
1.6	87.0	86.8	82.1
2.4	89.2	89.2	85.9
3.2	89.5	90.0	87.5
4.0	89.6	90.0	88.3
4.4	89.3	89.9	88.4
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-

Note: Slanted line shows the range of the rated load current.

Model	SFS204805
Item	Line Regulation
Object	+5V4A

## 1. Graph




Note: Slanted line shows the range of the rated input voltage.

Temperature 25°C  
Testing Circuitry Figure A

## 2. Values

Input Voltage [V]	Output Voltage [V]	
	Load 50%	Load 100%
34	5.037	4.985
36	5.036	4.986
40	5.038	4.993
48	5.049	5.001
55	5.049	4.999
60	5.049	4.996
70	5.047	4.992
76	5.046	4.990
78	5.046	4.990

Model	SFS204805	Temperature	25°C																																																			
Item	Load Regulation	Testing Circuitry	Figure A																																																			
Object	+5V4A																																																					
1.Graph	<p>Output Voltage [V]</p> <p>Load Current [A]</p> <p>Legend:</p> <ul style="list-style-type: none"> <li>Input Volt. 36V</li> <li>Input Volt. 48V</li> <li>Input Volt. 76V</li> </ul>																																																					
2.Values	<table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="3">Output Voltage [V]</th> </tr> <tr> <th>Input Volt. 36[V]</th> <th>Input Volt. 48[V]</th> <th>Input Volt. 76[V]</th> </tr> </thead> <tbody> <tr> <td>0.0</td> <td>5.088</td> <td>5.094</td> <td>5.096</td> </tr> <tr> <td>0.8</td> <td>5.066</td> <td>5.075</td> <td>5.075</td> </tr> <tr> <td>1.6</td> <td>5.045</td> <td>5.058</td> <td>5.056</td> </tr> <tr> <td>2.4</td> <td>5.026</td> <td>5.039</td> <td>5.036</td> </tr> <tr> <td>3.2</td> <td>5.007</td> <td>5.021</td> <td>5.013</td> </tr> <tr> <td>4.0</td> <td>4.987</td> <td>5.002</td> <td>4.991</td> </tr> <tr> <td>4.4</td> <td>4.976</td> <td>4.992</td> <td>4.979</td> </tr> <tr> <td>--</td> <td>-</td> <td>-</td> <td>-</td> </tr> </tbody> </table>			Load Current [A]	Output Voltage [V]			Input Volt. 36[V]	Input Volt. 48[V]	Input Volt. 76[V]	0.0	5.088	5.094	5.096	0.8	5.066	5.075	5.075	1.6	5.045	5.058	5.056	2.4	5.026	5.039	5.036	3.2	5.007	5.021	5.013	4.0	4.987	5.002	4.991	4.4	4.976	4.992	4.979	--	-	-	-	--	-	-	-	--	-	-	-	--	-	-	-
Load Current [A]	Output Voltage [V]																																																					
	Input Volt. 36[V]	Input Volt. 48[V]	Input Volt. 76[V]																																																			
0.0	5.088	5.094	5.096																																																			
0.8	5.066	5.075	5.075																																																			
1.6	5.045	5.058	5.056																																																			
2.4	5.026	5.039	5.036																																																			
3.2	5.007	5.021	5.013																																																			
4.0	4.987	5.002	4.991																																																			
4.4	4.976	4.992	4.979																																																			
--	-	-	-																																																			
--	-	-	-																																																			
--	-	-	-																																																			
--	-	-	-																																																			
Note:	Slanted line shows the range of the rated load current.																																																					

**COSEL**


**COSEL**

Model SFS204805

Item Ripple Voltage (by Load Current)

Object +5V4A

## 1. Graph

Temperature 25°C  
Testing Circuitry Figure C

## 2. Values

Load Current [A]	Ripple Voltage [mV]	
	Input Volt. 36 [V]	Input Volt. 76 [V]
0.0	3	4
0.8	3	4
1.6	4	5
2.4	4	5
3.2	4	5
4.0	4	5
4.4	4	5
--	-	-
--	-	-
--	-	-
--	-	-

Measured by 100MHz Ossiloscope.

Ripple Voltage is shown as p-p in the figure below.

Note: Slanted line shows the range of the rated load current.

Ripple [mVp-p]




Fig.Complex Ripple Wave Form


**COSEL**

Model SFS204805

Item Ripple-Noise

Object +5V4A

## 1. Graph



Measured by 100MHz Ossiloscope.

Ripple-Noise is shown as p-p in the figure below.

Note: Slanted line shows the range of the rated load current.

Temperature 25°C  
Testing Circuitry Figure C

## 2. Values

Load Current [A]	Ripple-Noise [mV]	
	Input Volt. 36 [V]	Input Volt. 76 [V]
0.0	12	9
0.8	9	9
1.6	8	9
2.4	8	9
3.2	8	10
4.0	9	11
4.4	9	11
---	-	-
---	-	-
---	-	-
---	-	-




Fig.Complex Ripple Noise Wave Form


**COSEL**

Model SFS204805

Item Ripple Voltage (by Ambient Temp.)

Object +5V4A

## 1. Graph



Measured by 100MHz Ossiloscope.


Note: Slanted line shows the range of the rated ambient temperature.

Testing Circuitry Figure C

## 2. Values

Ambient Temperature [°C]	Ripple Voltage [mV]	
	Load 50%	Load 100%
-50	6	6
-40	5	5
-20	5	5
0	5	5
25	4	4
85	4	4
90	4	4
--	-	-
--	-	-
--	-	-
--	-	-

Model	SFS204805
Item	Ambient Temperature Drift
Object	+5V4A



Note: Slanted line shows the range of the rated ambient temperature.

### Testing Circuitry Figure A

### 2.Values

Ambient Temperature [°C]	Output Voltage [V]		
	Input Volt. 36[V]	Input Volt. 48[V]	Input Volt. 76[V]
-45	4.973	4.992	4.979
-40	4.973	4.993	4.981
-20	4.977	4.997	4.986
0	4.983	5.003	4.992
25	4.990	5.005	4.994
50	4.991	5.004	4.991
85	4.989	4.999	4.973
90	4.989	4.996	4.971
--	-	-	-
--	-	-	-
--	-	-	-



Model	SFS204805
Item	Output Voltage Accuracy
Object	+5V4A

Testing Circuitry Figure A

### 1. Output Voltage Accuracy

This is defined as the value of the output voltage, regulation load, ambient temperature and input voltage varied at random in the range as specified below.

Temperature : -40 - 85°C

Input Voltage : 36 - 76V

Load Current : 0 - 4A

\* Output Voltage Accuracy =  $\pm(\text{Maximum of Output Voltage} - \text{Minimum of Output Voltage}) / 2$

$$\text{* Output Voltage Accuracy (Ration)} = \frac{\text{Output Voltage Accuracy}}{\text{Rated Output Voltage}} \times 100$$

### 2. Values

Item	Temperature [°C]	Input Voltage[V]	Output		Output Voltage Accuracy	
			Current[A]	Voltage[V]	Value [mV]	Ration [%]
Maximum Voltage	85	36	0	5.126	$\pm 77$	$\pm 1.5$
Minimum Voltage	85	76	4	4.973		


**COSEL**

Model SFS204805

Item Time Lapse Drift

Object +5V4A

## 1. Graph

Temperature 25°C  
Testing Circuitry Figure A

## 2. Values

Time since start [H]	Output Voltage [V]
0.0	5.004
0.5	5.001
1.0	5.001
2.0	5.001
3.0	5.001
4.0	5.001
5.0	5.001
6.0	5.001
7.0	5.001
8.0	5.001

**COSEL**

Model SFS204805


Item Rise and Fall Time

Object +5V4A

Temperature 25°C  
Testing Circuitry Figure A


## 1. Graph

Input Volt. 36 V




## 2. Values

Load	Time	Td	Tr	Ts	Th	Tf	[mS]
50 %		60.5	0.3	60.8	0.3	0.5	
100 %		60.5	0.4	60.9	0.3	0.5	



Model	SFS204805
Item	Minimum Input Voltage for Regulated Output Voltage
Object	+5V4A

## 1. Graph




Note: Slanted line shows the range of the rated ambient temperature.

## Testing Circuitry Figure A


## 2. Values

Ambient Temperature [°C]	Input Voltage [V]	
	Load 50%	Load 100%
-45	32.1	32.2
-40	32.2	32.2
-20	32.3	32.4
0	32.5	32.4
25	32.5	32.6
50	32.6	32.7
85	32.8	32.9
90	32.8	32.9
--	-	-
--	-	-
--	-	-

Model	SFS204805	Temperature	25°C																																																																							
Item	Overcurrent Protection	Testing Circuitry	Figure A																																																																							
Object	+5V4A																																																																									
1.Graph	Input Volt. 36V Input Volt. 48V Input Volt. 76V																																																																									
		2.Values																																																																								
		<table border="1"> <thead> <tr> <th rowspan="2">Output Voltage [V]</th> <th colspan="3">Load Current [A]</th> </tr> <tr> <th>36[V]</th> <th>48[V]</th> <th>76[V]</th> </tr> </thead> <tbody> <tr><td>5.00</td><td>4.04</td><td>4.18</td><td>4.05</td></tr> <tr><td>4.75</td><td>4.76</td><td>4.74</td><td>4.84</td></tr> <tr><td>4.50</td><td>4.76</td><td>4.75</td><td>4.88</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	Output Voltage [V]	Load Current [A]			36[V]	48[V]	76[V]	5.00	4.04	4.18	4.05	4.75	4.76	4.74	4.84	4.50	4.76	4.75	4.88	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
Output Voltage [V]	Load Current [A]																																																																									
	36[V]	48[V]	76[V]																																																																							
5.00	4.04	4.18	4.05																																																																							
4.75	4.76	4.74	4.84																																																																							
4.50	4.76	4.75	4.88																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
-	-	-	-																																																																							
		<p>Note: Slanted line shows the range of the rated load current.</p> <p>When the output voltage fell to less than 4.5V, the unit shuts off the output by operating low voltage protection.</p>																																																																								

Model	SFS204805
Item	Overvoltage Protection
Object	+5V4A

1. Graph      ─△─ Input Volt. 48V



Testing Circuitry Figure A

2. Values

Ambient Temperature [°C]	Operating Point [V]		
	Input Volt. 48[V]	Input Volt.	Input Volt.
-40	6.68	-	-
25	6.58	-	-
85	6.47	-	-
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-
--	-	-	-
-	-	-	-

Note: Slanted line shows the range of the rated ambient temperature.




Figure A




Figure B (General Electric Characteristic)




Figure C (Ripple and Ripple noise Characteristic)