



TEST DATA OF SUS100505 SUCS100505

Regulated DC Power Supply
Mar 28, 2005

Approved by : Tetsuo Sugimori
Tetsuo Sugimori Design Manager

Prepared by : Yoshimichi Hirokawa
Yoshimichi Hirokawa Design Engineer

COSEL CO.,LTD.

CONTENTS

1. Input Current (by Input Voltage) 1
 2. Input Current (by Load Current) 2
 3. Input Power (by Load Current) 3
 4. Efficiency (by Input Voltage) 4
 5. Efficiency (by Load Current) 5
 6. Line Regulation 6
 7. Load Regulation 7
 8. Dynamic Load Response 8
 9. Ripple Voltage (by Load Current) 9
 10. Ripple-Noise 10
 11. Ripple Voltage (by Ambient Temperature) 11
 12. Ambient Temperature Drift 12
 13. Output Voltage Accuracy 13
 14. Time Lapse Drift 14
 15. Rise and Fall Time 15
 16. Minimum Input Voltage for Regulated Output Voltage 16
 17. Overcurrent Protection 17
 18. Figure of Testing Circuitry 18

(Final Page 18)



Model		SUS100505/SUCS100505		Temperature 25°C																																																																																
Item		Input Current (by Input Voltage)		Testing Circuitry Figure A																																																																																
Object		_____																																																																																		
1.Graph			—△— Load 100% - - - □ - - Load 50% - · - ○ - · - Load 0%																																																																																	
			2.Values																																																																																	
			<table border="1"> <thead> <tr> <th rowspan="2">Input Voltage [V]</th> <th colspan="3">Input Current [A]</th> </tr> <tr> <th>Load 0%</th> <th>Load 50%</th> <th>Load 100%</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>0.000</td><td>0.000</td><td>0.000</td></tr> <tr><td>1.70</td><td>0.000</td><td>0.000</td><td>0.000</td></tr> <tr><td>2.00</td><td>0.000</td><td>0.000</td><td>0.000</td></tr> <tr><td>3.00</td><td>0.000</td><td>0.000</td><td>0.000</td></tr> <tr><td>4.00</td><td>0.000</td><td>0.000</td><td>0.000</td></tr> <tr><td>4.16</td><td>0.082</td><td>1.433</td><td>2.888</td></tr> <tr><td>4.50</td><td>0.077</td><td>1.363</td><td>2.699</td></tr> <tr><td>5.00</td><td>0.075</td><td>1.227</td><td>2.402</td></tr> <tr><td>6.00</td><td>0.071</td><td>1.025</td><td>1.988</td></tr> <tr><td>7.00</td><td>0.070</td><td>0.895</td><td>1.690</td></tr> <tr><td>8.00</td><td>0.070</td><td>0.795</td><td>1.481</td></tr> <tr><td>9.00</td><td>0.071</td><td>0.716</td><td>1.322</td></tr> <tr><td>10.00</td><td>0.076</td><td>0.650</td><td>1.210</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>			Input Voltage [V]	Input Current [A]			Load 0%	Load 50%	Load 100%	0.00	0.000	0.000	0.000	1.70	0.000	0.000	0.000	2.00	0.000	0.000	0.000	3.00	0.000	0.000	0.000	4.00	0.000	0.000	0.000	4.16	0.082	1.433	2.888	4.50	0.077	1.363	2.699	5.00	0.075	1.227	2.402	6.00	0.071	1.025	1.988	7.00	0.070	0.895	1.690	8.00	0.070	0.795	1.481	9.00	0.071	0.716	1.322	10.00	0.076	0.650	1.210	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
Input Voltage [V]	Input Current [A]																																																																																			
	Load 0%	Load 50%	Load 100%																																																																																	
0.00	0.000	0.000	0.000																																																																																	
1.70	0.000	0.000	0.000																																																																																	
2.00	0.000	0.000	0.000																																																																																	
3.00	0.000	0.000	0.000																																																																																	
4.00	0.000	0.000	0.000																																																																																	
4.16	0.082	1.433	2.888																																																																																	
4.50	0.077	1.363	2.699																																																																																	
5.00	0.075	1.227	2.402																																																																																	
6.00	0.071	1.025	1.988																																																																																	
7.00	0.070	0.895	1.690																																																																																	
8.00	0.070	0.795	1.481																																																																																	
9.00	0.071	0.716	1.322																																																																																	
10.00	0.076	0.650	1.210																																																																																	
-	-	-	-																																																																																	
-	-	-	-																																																																																	
-	-	-	-																																																																																	
-	-	-	-																																																																																	
-	-	-	-																																																																																	
Note: Slanted line shows the range of the rated input voltage.																																																																																				



Model		SUS100505/SUCS100505		Temperature 25°C Testing Circuitry Figure A																																																			
Item		Input Current (by Load Current)																																																					
Object		_____																																																					
1. Graph <div style="float: right; margin-left: 20px;"> —△— Input Volt. 4.5V - - - □ - - Input Volt. 5V - · - ○ - · - Input Volt. 9V </div>			2. Values																																																				
<p style="font-size: small;">Note: Slanted line shows the range of the rated load current.</p>			<table border="1" style="width: 100%; border-collapse: collapse; text-align: center;"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="3">Input Current [A]</th> </tr> <tr> <th>Input Volt. 4.5[V]</th> <th>Input Volt. 5[V]</th> <th>Input Volt. 9[V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>0.077</td><td>0.072</td><td>0.072</td></tr> <tr><td>0.4</td><td>0.575</td><td>0.514</td><td>0.327</td></tr> <tr><td>0.8</td><td>1.105</td><td>1.011</td><td>0.569</td></tr> <tr><td>1.2</td><td>1.611</td><td>1.441</td><td>0.845</td></tr> <tr><td>1.6</td><td>2.189</td><td>1.940</td><td>1.091</td></tr> <tr><td>2.0</td><td>2.685</td><td>2.369</td><td>1.347</td></tr> <tr><td>2.2</td><td>3.000</td><td>2.636</td><td>1.461</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>		Load Current [A]	Input Current [A]			Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]	0.0	0.077	0.072	0.072	0.4	0.575	0.514	0.327	0.8	1.105	1.011	0.569	1.2	1.611	1.441	0.845	1.6	2.189	1.940	1.091	2.0	2.685	2.369	1.347	2.2	3.000	2.636	1.461	--	-	-	-	--	-	-	-	--	-	-	-	--	-	-	-
Load Current [A]	Input Current [A]																																																						
	Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]																																																				
0.0	0.077	0.072	0.072																																																				
0.4	0.575	0.514	0.327																																																				
0.8	1.105	1.011	0.569																																																				
1.2	1.611	1.441	0.845																																																				
1.6	2.189	1.940	1.091																																																				
2.0	2.685	2.369	1.347																																																				
2.2	3.000	2.636	1.461																																																				
--	-	-	-																																																				
--	-	-	-																																																				
--	-	-	-																																																				
--	-	-	-																																																				



COSEL																																																						
Model	SUS100505/SUCS100505	Temperature	25°C																																																			
Item	Input Power (by Load Current)	Testing Circuitry	Figure A																																																			
Object	_____																																																					
1.Graph	<p> △ Input Volt. 4.5V □ Input Volt. 5V ○ Input Volt. 9V </p>	2.Values																																																				
		<table border="1" style="width: 100%; border-collapse: collapse; text-align: center;"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="3">Input Power [W]</th> </tr> <tr> <th>Input Volt. 4.5[V]</th> <th>Input Volt. 5[V]</th> <th>Input Volt. 9[V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>0.35</td><td>0.37</td><td>0.65</td></tr> <tr><td>0.4</td><td>2.55</td><td>2.58</td><td>2.95</td></tr> <tr><td>0.8</td><td>4.93</td><td>4.99</td><td>5.13</td></tr> <tr><td>1.2</td><td>7.20</td><td>7.20</td><td>7.57</td></tr> <tr><td>1.6</td><td>9.59</td><td>9.57</td><td>9.75</td></tr> <tr><td>2.0</td><td>12.05</td><td>11.94</td><td>11.97</td></tr> <tr><td>2.2</td><td>13.38</td><td>13.21</td><td>13.12</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>		Load Current [A]	Input Power [W]			Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]	0.0	0.35	0.37	0.65	0.4	2.55	2.58	2.95	0.8	4.93	4.99	5.13	1.2	7.20	7.20	7.57	1.6	9.59	9.57	9.75	2.0	12.05	11.94	11.97	2.2	13.38	13.21	13.12	--	-	-	-	--	-	-	-	--	-	-	-	--	-	-	-
Load Current [A]	Input Power [W]																																																					
	Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]																																																			
0.0	0.35	0.37	0.65																																																			
0.4	2.55	2.58	2.95																																																			
0.8	4.93	4.99	5.13																																																			
1.2	7.20	7.20	7.57																																																			
1.6	9.59	9.57	9.75																																																			
2.0	12.05	11.94	11.97																																																			
2.2	13.38	13.21	13.12																																																			
--	-	-	-																																																			
--	-	-	-																																																			
--	-	-	-																																																			
--	-	-	-																																																			
<p>Note: Slanted line shows the range of the rated load current.</p>																																																						



Model		SUS100505/SUCS100505																																	
Item		Efficiency (by Input Voltage)																																	
Object		_____																																	
1.Graph		Temperature 25°C Testing Circuitry Figure A																																	
<p>---□--- Load 50% —△— Load 100%</p> <p>Efficiency [%]</p> <p>Input Voltage [V]</p> <p>Note: Slanted line shows the range of the rated input voltage.</p>		2.Values																																	
		<table border="1"> <thead> <tr> <th rowspan="2">Input Voltage [V]</th> <th colspan="2">Efficiency [%]</th> </tr> <tr> <th>Load 50%</th> <th>Load 100%</th> </tr> </thead> <tbody> <tr> <td>4.0</td> <td>83.1</td> <td>82.6</td> </tr> <tr> <td>4.5</td> <td>82.8</td> <td>83.2</td> </tr> <tr> <td>5.0</td> <td>82.7</td> <td>84.0</td> </tr> <tr> <td>6.0</td> <td>81.6</td> <td>84.5</td> </tr> <tr> <td>7.0</td> <td>80.4</td> <td>84.6</td> </tr> <tr> <td>8.0</td> <td>78.9</td> <td>84.3</td> </tr> <tr> <td>9.0</td> <td>77.7</td> <td>83.8</td> </tr> <tr> <td>10.0</td> <td>76.7</td> <td>83.0</td> </tr> <tr> <td>-</td> <td>-</td> <td>-</td> </tr> </tbody> </table>		Input Voltage [V]	Efficiency [%]		Load 50%	Load 100%	4.0	83.1	82.6	4.5	82.8	83.2	5.0	82.7	84.0	6.0	81.6	84.5	7.0	80.4	84.6	8.0	78.9	84.3	9.0	77.7	83.8	10.0	76.7	83.0	-	-	-
Input Voltage [V]	Efficiency [%]																																		
	Load 50%	Load 100%																																	
4.0	83.1	82.6																																	
4.5	82.8	83.2																																	
5.0	82.7	84.0																																	
6.0	81.6	84.5																																	
7.0	80.4	84.6																																	
8.0	78.9	84.3																																	
9.0	77.7	83.8																																	
10.0	76.7	83.0																																	
-	-	-																																	



Model		SUS100505/SUCS100505		Temperature 25°C																																																				
Item		Efficiency (by Load Current)		Testing Circuitry Figure A																																																				
Object		_____																																																						
1. Graph		—△— Input Volt. 4.5V - - - □ - - Input Volt. 5V - · - ○ - · - Input Volt. 9V		2. Values																																																				
				<table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="3">Efficiency [%]</th> </tr> <tr> <th>Input Volt. 4.5[V]</th> <th>Input Volt. 5[V]</th> <th>Input Volt. 9[V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>0.4</td><td>78.5</td><td>77.5</td><td>67.8</td></tr> <tr><td>0.8</td><td>81.3</td><td>80.3</td><td>78.2</td></tr> <tr><td>1.2</td><td>83.6</td><td>83.5</td><td>79.5</td></tr> <tr><td>1.6</td><td>83.6</td><td>83.8</td><td>82.2</td></tr> <tr><td>2.0</td><td>83.1</td><td>83.9</td><td>83.7</td></tr> <tr><td>2.2</td><td>82.4</td><td>83.5</td><td>84.0</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>		Load Current [A]	Efficiency [%]			Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]	0.0	-	-	-	0.4	78.5	77.5	67.8	0.8	81.3	80.3	78.2	1.2	83.6	83.5	79.5	1.6	83.6	83.8	82.2	2.0	83.1	83.9	83.7	2.2	82.4	83.5	84.0	--	-	-	-	--	-	-	-	--	-	-	-	--	-	-	-
Load Current [A]	Efficiency [%]																																																							
	Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]																																																					
0.0	-	-	-																																																					
0.4	78.5	77.5	67.8																																																					
0.8	81.3	80.3	78.2																																																					
1.2	83.6	83.5	79.5																																																					
1.6	83.6	83.8	82.2																																																					
2.0	83.1	83.9	83.7																																																					
2.2	82.4	83.5	84.0																																																					
--	-	-	-																																																					
--	-	-	-																																																					
--	-	-	-																																																					
--	-	-	-																																																					
Note: Slanted line shows the range of the rated load current.																																																								



COSEL																																			
Model	SUS100505/SUCS100505	Temperature	25°C																																
Item	Line Regulation	Testing Circuitry	Figure A																																
Object	+5V2A																																		
<p>1. Graph</p> <div style="text-align: right;"> <p>---□--- Load 50%</p> <p>—△— Load 100%</p> </div> <p style="text-align: center;">Input Voltage [V]</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Input Voltage [V]</th> <th colspan="2">Output Voltage [V]</th> </tr> <tr> <th>Load 50%</th> <th>Load 100%</th> </tr> </thead> <tbody> <tr><td>4.0</td><td>5.004</td><td>5.000</td></tr> <tr><td>4.5</td><td>5.005</td><td>5.000</td></tr> <tr><td>5.0</td><td>5.005</td><td>5.000</td></tr> <tr><td>6.0</td><td>5.005</td><td>5.001</td></tr> <tr><td>7.0</td><td>5.005</td><td>5.001</td></tr> <tr><td>8.0</td><td>5.005</td><td>5.001</td></tr> <tr><td>9.0</td><td>5.005</td><td>5.001</td></tr> <tr><td>10.0</td><td>5.005</td><td>5.002</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> </tbody> </table>		Input Voltage [V]	Output Voltage [V]		Load 50%	Load 100%	4.0	5.004	5.000	4.5	5.005	5.000	5.0	5.005	5.000	6.0	5.005	5.001	7.0	5.005	5.001	8.0	5.005	5.001	9.0	5.005	5.001	10.0	5.005	5.002	--	-	-
Input Voltage [V]	Output Voltage [V]																																		
	Load 50%	Load 100%																																	
4.0	5.004	5.000																																	
4.5	5.005	5.000																																	
5.0	5.005	5.000																																	
6.0	5.005	5.001																																	
7.0	5.005	5.001																																	
8.0	5.005	5.001																																	
9.0	5.005	5.001																																	
10.0	5.005	5.002																																	
--	-	-																																	
<p>Note: Slanted line shows the range of the rated input voltage.</p>																																			




Model		SUS100505/SUCS100505		Temperature 25°C Testing Circuitry Figure A																																																					
Item		Load Regulation																																																							
Object		+5V2A																																																							
1. Graph			—△— Input Volt. 4.5V - - - □ - - Input Volt. 5V · · · ○ · · · Input Volt. 9V	2. Values																																																					
Output Voltage [V]				<table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="3">Output Voltage [V]</th> </tr> <tr> <th>Input Volt. 4.5[V]</th> <th>Input Volt. 5[V]</th> <th>Input Volt. 9[V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>5.007</td><td>5.007</td><td>5.007</td></tr> <tr><td>0.4</td><td>5.006</td><td>5.006</td><td>5.006</td></tr> <tr><td>0.8</td><td>5.005</td><td>5.005</td><td>5.005</td></tr> <tr><td>1.2</td><td>5.004</td><td>5.004</td><td>5.004</td></tr> <tr><td>1.6</td><td>5.002</td><td>5.003</td><td>5.003</td></tr> <tr><td>2.0</td><td>5.000</td><td>5.001</td><td>5.002</td></tr> <tr><td>2.2</td><td>4.999</td><td>5.000</td><td>5.001</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>			Load Current [A]	Output Voltage [V]			Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]	0.0	5.007	5.007	5.007	0.4	5.006	5.006	5.006	0.8	5.005	5.005	5.005	1.2	5.004	5.004	5.004	1.6	5.002	5.003	5.003	2.0	5.000	5.001	5.002	2.2	4.999	5.000	5.001	--	-	-	-	--	-	-	-	--	-	-	-	--	-	-	-
				Load Current [A]	Output Voltage [V]																																																				
					Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]																																																		
				0.0	5.007	5.007	5.007																																																		
				0.4	5.006	5.006	5.006																																																		
				0.8	5.005	5.005	5.005																																																		
				1.2	5.004	5.004	5.004																																																		
				1.6	5.002	5.003	5.003																																																		
				2.0	5.000	5.001	5.002																																																		
				2.2	4.999	5.000	5.001																																																		
				--	-	-	-																																																		
				--	-	-	-																																																		
--	-	-	-																																																						
--	-	-	-																																																						
Note: Slanted line shows the range of the rated load current.																																																									




Model	SUS100505/SUCS100505	Temperature	25°C
Item	Dynamic Load Response	Testing Circuitry	Figure A
Object	+5V2A		

Input Volt. 5 V
Cycle 100 mS



Min. Load (0A) \longleftrightarrow
Load 100% (2A)




200µs/div




200µs/div

Min. Load (0A) \longleftrightarrow
Load 50% (1A)




200µs/div




200µs/div

Load 50% (1A) \longleftrightarrow
Load 100% (2A)



200µs/div



200µs/div



<p>Model SUS100505/SUCS100505</p>		<p>Temperature 25°C Testing Circuitry Figure B</p>																																						
<p>Item Ripple Voltage (by Load Current)</p>																																								
<p>Object +5V2A</p>		<p>2.Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="2">Ripple Voltage [mV]</th> </tr> <tr> <th>Input Volt. 4.5 [V]</th> <th>Input Volt. 9 [V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>3</td><td>2</td></tr> <tr><td>0.4</td><td>6</td><td>7</td></tr> <tr><td>0.8</td><td>9</td><td>10</td></tr> <tr><td>1.2</td><td>14</td><td>12</td></tr> <tr><td>1.6</td><td>19</td><td>14</td></tr> <tr><td>2.0</td><td>24</td><td>17</td></tr> <tr><td>2.2</td><td>25</td><td>18</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> </tbody> </table>	Load Current [A]	Ripple Voltage [mV]		Input Volt. 4.5 [V]	Input Volt. 9 [V]	0.0	3	2	0.4	6	7	0.8	9	10	1.2	14	12	1.6	19	14	2.0	24	17	2.2	25	18	--	-	-	--	-	-	--	-	-	--	-	-
Load Current [A]	Ripple Voltage [mV]																																							
	Input Volt. 4.5 [V]	Input Volt. 9 [V]																																						
0.0	3	2																																						
0.4	6	7																																						
0.8	9	10																																						
1.2	14	12																																						
1.6	19	14																																						
2.0	24	17																																						
2.2	25	18																																						
--	-	-																																						
--	-	-																																						
--	-	-																																						
--	-	-																																						
<p>1.Graph</p> <p> —△— Input Volt. 4.5V - - ○ - - Input Volt. 9V </p> <p>Measured by 100 MHz Oscilloscope. Ripple Voltage is shown as p-p in the figure below. Note: Slanted line shows the range of the rated load current.</p> <p>Ripple [mVp-p]</p> <p>Fig.Complex Ripple Wave Form</p>																																								



<p>Model SUS100505/SUCS100505</p>		<p>Temperature 25°C Testing Circuitry Figure B</p>																																						
<p>Item Ripple-Noise</p>																																								
<p>Object +5V2A</p>																																								
<p>1. Graph</p> <div style="text-align: center;"> <p>—△— Input Volt. 4.5V - -○- - Input Volt. 9V</p> </div> <p>Measured by 100 MHz Oscilloscope. Ripple-Noise is shown as p-p in the figure below. Note: Slanted line shows the range of the rated load current.</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="2">Ripple-Noise [mV]</th> </tr> <tr> <th>Input Volt. 4.5 [V]</th> <th>Input Volt. 9 [V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>7</td><td>7</td></tr> <tr><td>0.4</td><td>8</td><td>10</td></tr> <tr><td>0.8</td><td>13</td><td>13</td></tr> <tr><td>1.2</td><td>18</td><td>16</td></tr> <tr><td>1.6</td><td>23</td><td>20</td></tr> <tr><td>2.0</td><td>28</td><td>23</td></tr> <tr><td>2.2</td><td>32</td><td>25</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> </tbody> </table>	Load Current [A]	Ripple-Noise [mV]		Input Volt. 4.5 [V]	Input Volt. 9 [V]	0.0	7	7	0.4	8	10	0.8	13	13	1.2	18	16	1.6	23	20	2.0	28	23	2.2	32	25	--	-	-	--	-	-	--	-	-	--	-	-
Load Current [A]	Ripple-Noise [mV]																																							
	Input Volt. 4.5 [V]	Input Volt. 9 [V]																																						
0.0	7	7																																						
0.4	8	10																																						
0.8	13	13																																						
1.2	18	16																																						
1.6	23	20																																						
2.0	28	23																																						
2.2	32	25																																						
--	-	-																																						
--	-	-																																						
--	-	-																																						
--	-	-																																						
<p>Fig. Complex Ripple Noise Wave Form</p>																																								



Model		SUS100505/SUCS100505																																							
Item		Ripple Voltage (by Ambient Temp.)																																							
Object		+5V2A																																							
1. Graph		Testing Circuitry Figure B																																							
<p> ---□--- Load 50% —△— Load 100% </p> <p> Ambient Temperature [°C] Input Volt. 5V </p>		2. Values																																							
		<table border="1"> <thead> <tr> <th rowspan="2">Ambient Temperature [°C]</th> <th colspan="2">Ripple Voltage [mV]</th> </tr> <tr> <th>Load 50%</th> <th>Load 100%</th> </tr> </thead> <tbody> <tr><td>-60</td><td>24</td><td>39</td></tr> <tr><td>-40</td><td>21</td><td>36</td></tr> <tr><td>-20</td><td>20</td><td>34</td></tr> <tr><td>0</td><td>17</td><td>31</td></tr> <tr><td>25</td><td>15</td><td>28</td></tr> <tr><td>55</td><td>13</td><td>23</td></tr> <tr><td>60</td><td>12</td><td>22</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> </tbody> </table>		Ambient Temperature [°C]	Ripple Voltage [mV]		Load 50%	Load 100%	-60	24	39	-40	21	36	-20	20	34	0	17	31	25	15	28	55	13	23	60	12	22	--	-	-	--	-	-	--	-	-	--	-	-
Ambient Temperature [°C]	Ripple Voltage [mV]																																								
	Load 50%	Load 100%																																							
-60	24	39																																							
-40	21	36																																							
-20	20	34																																							
0	17	31																																							
25	15	28																																							
55	13	23																																							
60	12	22																																							
--	-	-																																							
--	-	-																																							
--	-	-																																							
--	-	-																																							
<p>Measured by 100 MHz Oscilloscope.</p> <p>Note: Slanted line shows the range of the rated ambient temperature.</p>																																									



COSEL																																																						
Model	SUS100505/SUCS100505																																																					
Item	Ambient Temperature Drift	Testing Circuitry Figure A																																																				
Object	+5V2A																																																					
1. Graph	<p> —△— Input Volt. 4.5V - - - □ - - - Input Volt. 5V - · - ○ - · - - Input Volt. 9V </p> <p style="text-align: center;">Ambient Temperature [°C] Load 100%</p>	2. Values																																																				
		<table border="1"> <thead> <tr> <th rowspan="2">Ambient Temperature [°C]</th> <th colspan="3">Output Voltage [V]</th> </tr> <tr> <th>Input Volt. 4.5[V]</th> <th>Input Volt. 5[V]</th> <th>Input Volt. 9[V]</th> </tr> </thead> <tbody> <tr><td>-60</td><td>4.999</td><td>5.000</td><td>5.001</td></tr> <tr><td>-40</td><td>5.003</td><td>5.004</td><td>5.004</td></tr> <tr><td>-20</td><td>5.004</td><td>5.005</td><td>5.005</td></tr> <tr><td>0</td><td>5.003</td><td>5.003</td><td>5.004</td></tr> <tr><td>25</td><td>4.999</td><td>4.998</td><td>4.999</td></tr> <tr><td>55</td><td>4.992</td><td>4.992</td><td>4.993</td></tr> <tr><td>60</td><td>4.991</td><td>4.990</td><td>4.991</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	Ambient Temperature [°C]	Output Voltage [V]			Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]	-60	4.999	5.000	5.001	-40	5.003	5.004	5.004	-20	5.004	5.005	5.005	0	5.003	5.003	5.004	25	4.999	4.998	4.999	55	4.992	4.992	4.993	60	4.991	4.990	4.991	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
Ambient Temperature [°C]	Output Voltage [V]																																																					
	Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]																																																			
-60	4.999	5.000	5.001																																																			
-40	5.003	5.004	5.004																																																			
-20	5.004	5.005	5.005																																																			
0	5.003	5.003	5.004																																																			
25	4.999	4.998	4.999																																																			
55	4.992	4.992	4.993																																																			
60	4.991	4.990	4.991																																																			
-	-	-	-																																																			
-	-	-	-																																																			
-	-	-	-																																																			
-	-	-	-																																																			
<p>Note: Slanted line shows the range of the rated ambient temperature.</p>																																																						



COSEL		
Model	SUS100505/SUCS100505	
Item	Output Voltage Accuracy	Testing Circuitry Figure A
Object	+5V2A	

1. Output Voltage Accuracy

This is defined as the value of the output voltage, regulation load, ambient temperature and input voltage varied at random in the range as specified below.

Temperature : -40 - 55°C

Input Voltage : 4.5 - 9V

Load Current : 0 - 2A

* Output Voltage Accuracy = $\pm(\text{Maximum of Output Voltage} - \text{Minimum of Output Voltage}) / 2$

* Output Voltage Accuracy (Ration) = $\frac{\text{Output Voltage Accuracy}}{\text{Rated Output Voltage}} \times 100$

2. Values

Item	Temperature [°C]	Input Voltage[V]	Output		Output Voltage Accuracy	
			Current[A]	Voltage[V]	Value [mV]	Ration [%]
Maximum Voltage	-20	4.5	0	5.011	±10	±0.2
Minimum Voltage	55	5	2	4.992		




COSEL																								
Model	SUS100505/SUCS100505																							
Item	Time Lapse Drift	Temperature 25°C Testing Circuitry Figure A																						
Object	+5V2A																							
<p>1. Graph</p> <p style="text-align: center;">Time [H]</p> <p>Input Volt. 5V Load 100%</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th>Time since start [H]</th> <th>Output Voltage [V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>5.005</td></tr> <tr><td>0.5</td><td>5.004</td></tr> <tr><td>1.0</td><td>5.004</td></tr> <tr><td>2.0</td><td>5.004</td></tr> <tr><td>3.0</td><td>5.004</td></tr> <tr><td>4.0</td><td>5.004</td></tr> <tr><td>5.0</td><td>5.004</td></tr> <tr><td>6.0</td><td>5.004</td></tr> <tr><td>7.0</td><td>5.004</td></tr> <tr><td>8.0</td><td>5.004</td></tr> </tbody> </table>	Time since start [H]	Output Voltage [V]	0.0	5.005	0.5	5.004	1.0	5.004	2.0	5.004	3.0	5.004	4.0	5.004	5.0	5.004	6.0	5.004	7.0	5.004	8.0	5.004
Time since start [H]	Output Voltage [V]																							
0.0	5.005																							
0.5	5.004																							
1.0	5.004																							
2.0	5.004																							
3.0	5.004																							
4.0	5.004																							
5.0	5.004																							
6.0	5.004																							
7.0	5.004																							
8.0	5.004																							



Model		SUS100505/SUCS100505	
Item		Rise and Fall Time	
Object		+5V2A	
		Temperature 25°C Testing Circuitry Figure A	


1. Graph

Input Volt. 5 V




2. Values

		[mS]				
Load \ Time	Time	Td	Tr	Ts	Th	Tf
50 %		0.5	0.9	1.4	0.2	0.7
100 %		0.5	1.0	1.5	0.1	0.3





Model	SUS100505/SUCS100505	Testing Circuitry Figure A
Item	Minimum Input Voltage for Regulated Output Voltage	
Object	+5V2A	



2. Values

Ambient Temperature [°C]	Input Voltage [V]	
	Load 50%	Load 100%
-60	2.5	3.2
-40	2.6	3.3
-20	2.7	3.4
0	2.7	3.4
25	2.8	3.6
55	2.9	3.6
60	3.0	3.6
-	-	-
-	-	-
-	-	-
-	-	-

Note: Slanted line shows the range of the rated ambient temperature.



Model SUS100505/SUCS100505		Temperature 25°C Testing Circuitry Figure A																																																							
Item	Overcurrent Protection																																																								
Object	+5V2A																																																								
<p>1.Graph</p> <p> Input Volt. 4.5V Input Volt. 5V Input Volt. 9V </p> <p>Output Voltage [V]</p> <p>Load Current [A]</p> <p>Note: Slanted line shows the range of the rated load current.</p>		<p>2.Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Output Voltage [V]</th> <th colspan="3">Load Current [A]</th> </tr> <tr> <th>Input Volt. 4.5[V]</th> <th>Input Volt. 5[V]</th> <th>Input Volt. 9[V]</th> </tr> </thead> <tbody> <tr><td>5.00</td><td>2.31</td><td>2.39</td><td>2.66</td></tr> <tr><td>4.75</td><td>2.38</td><td>2.48</td><td>2.80</td></tr> <tr><td>4.50</td><td>2.41</td><td>2.50</td><td>2.82</td></tr> <tr><td>4.00</td><td>2.40</td><td>2.48</td><td>2.75</td></tr> <tr><td>3.50</td><td>2.39</td><td>2.45</td><td>2.68</td></tr> <tr><td>3.00</td><td>2.38</td><td>2.45</td><td>2.63</td></tr> <tr><td>2.50</td><td>2.39</td><td>2.46</td><td>2.60</td></tr> <tr><td>2.00</td><td>2.43</td><td>2.49</td><td>2.57</td></tr> <tr><td>1.50</td><td>2.48</td><td>2.55</td><td>2.53</td></tr> <tr><td>1.00</td><td>2.59</td><td>2.65</td><td>2.51</td></tr> <tr><td>0.50</td><td>2.75</td><td>2.78</td><td>2.56</td></tr> <tr><td>0.00</td><td>3.29</td><td>3.36</td><td>3.03</td></tr> </tbody> </table>	Output Voltage [V]	Load Current [A]			Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]	5.00	2.31	2.39	2.66	4.75	2.38	2.48	2.80	4.50	2.41	2.50	2.82	4.00	2.40	2.48	2.75	3.50	2.39	2.45	2.68	3.00	2.38	2.45	2.63	2.50	2.39	2.46	2.60	2.00	2.43	2.49	2.57	1.50	2.48	2.55	2.53	1.00	2.59	2.65	2.51	0.50	2.75	2.78	2.56	0.00	3.29	3.36	3.03
Output Voltage [V]	Load Current [A]																																																								
	Input Volt. 4.5[V]	Input Volt. 5[V]	Input Volt. 9[V]																																																						
5.00	2.31	2.39	2.66																																																						
4.75	2.38	2.48	2.80																																																						
4.50	2.41	2.50	2.82																																																						
4.00	2.40	2.48	2.75																																																						
3.50	2.39	2.45	2.68																																																						
3.00	2.38	2.45	2.63																																																						
2.50	2.39	2.46	2.60																																																						
2.00	2.43	2.49	2.57																																																						
1.50	2.48	2.55	2.53																																																						
1.00	2.59	2.65	2.51																																																						
0.50	2.75	2.78	2.56																																																						
0.00	3.29	3.36	3.03																																																						




Figure A




Figure B(Ripple and Ripple noise Characteristic)