



# TEST DATA OF ZTW32412

(24.0V INPUT)

Regulated DC Power Supply

Date : Mar. 5. 1998

Approved by : N. Shiraishi  
Design Manager

Prepared by : T. Tsunoi  
Design Engineer


**コーセル株式会社**

**COSEL CO., LTD.**

CONTENTS

1. Line Regulation . . . . .	1
静的入力変動	
2. Efficiency . . . . .	2
効率	
3. Load Regulation . . . . .	3
静的負荷変動	
4. Ripple Voltage (by Load Current) . . . . .	4
リップル電圧(負荷電流特性)	
5. Ripple-Noise . . . . .	6
リップルノイズ	
6. Overcurrent Protection . . . . .	8
過電流保護	
7. Dynamic Load Responce . . . . .	9
動的負荷変動	
8. Rise and Fall Time . . . . .	11
立上り、立下がり時間	
9. Ambient Temperature Drift . . . . .	13
周囲温度変動	
10. Minimum Input Voltage for Regulated Output Voltage . . . . .	14
最低レギュレーション電圧	
11. Ripple Voltage (by Ambient Temperature) . . . . .	15
リップル電圧(周囲温度特性)	
12. Time Lapse Drift . . . . .	16
経時ドリフト	
13. Output Voltage Accuracy . . . . .	17
定電圧精度	
14. Condensation . . . . .	18
結露特性	
15. Figure of Testing Circuitry . . . . .	20
測定回路図	


(Final Page 20)



Temperature 25°C  
 Testing Circuitry Figure A

2. Values

Input Voltage [V]	Load 50%	Load 100%
	Output Volt. [V]	Output Volt. [V]
16.0	12.148	12.019
18.0	12.142	12.026
20.0	12.138	12.031
24.0	12.133	12.035
30.0	12.127	12.035
36.0	12.121	12.031
40.0	12.118	12.027
—	—	—
—	—	—
—	—	—
—	—	—
—	—	—



2. Values


Input Voltage [V]	Load 50%	Load 100%
	Output Volt. [V]	Output Volt. [V]
16.0	-12.135	-12.006
18.0	-12.129	-12.012
20.0	-12.125	-12.016
24.0	-12.119	-12.020
30.0	-12.112	-12.020
36.0	-12.106	-12.014
40.0	-12.103	-12.011
—	—	—
—	—	—
—	—	—
—	—	—
—	—	—



Model	ZTW32412
Item	Efficiency 効率
Object	

Temperature 25°C  
Testing Circuitry Figure A

1. Graph



Note: Slanted line shows the range of the rated input voltage.

(注) 斜線は定格入力電圧範囲を示す。

2. Values

Input Voltage [V]	Load 50%	Load 100%
	Efficiency [%]	Efficiency [%]
16.0	70.2	76.3
18.0	69.0	75.4
20.0	67.6	75.2
24.0	65.7	73.6
30.0	62.4	71.7
36.0	59.6	70.0
40.0	57.6	68.4
—	—	—
—	—	—
—	—	—
—	—	—
—	—	—



<b>Model</b> ZTW32412		Temperature      25°C																																																
<b>Item</b> Load Regulation  静的負荷変動		Testing Circuitry    Figure A																																																
<b>Object</b> +12V0.13A																																																		
<p>1. Graph</p> <div style="display: flex; justify-content: space-between; align-items: flex-start;"> <div style="width: 45%;"> </div> <div style="width: 45%;"> <p>—△—    Input Volt. 18.0V</p> <p>—□—    Input Volt. 24.0V</p> <p>—○—    Input Volt. 36.0V</p> </div> </div>	<p>2. Values</p> <table border="1" style="width:100%; border-collapse: collapse; text-align: center;"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th>Input Volt. 18.0[V]</th> <th>Input Volt. 24.0[V]</th> <th>Input Volt. 36.0[V]</th> </tr> <tr> <th>Output Volt. [V]</th> <th>Output Volt. [V]</th> <th>Output Volt. [V]</th> </tr> </thead> <tbody> <tr><td>0.000</td><td>12.302</td><td>12.306</td><td>12.315</td></tr> <tr><td>0.020</td><td>12.220</td><td>12.212</td><td>12.205</td></tr> <tr><td>0.040</td><td>12.179</td><td>12.170</td><td>12.160</td></tr> <tr><td>0.060</td><td>12.145</td><td>12.137</td><td>12.126</td></tr> <tr><td>0.080</td><td>12.112</td><td>12.107</td><td>12.097</td></tr> <tr><td>0.100</td><td>12.078</td><td>12.078</td><td>12.069</td></tr> <tr><td>0.120</td><td>12.042</td><td>12.048</td><td>12.042</td></tr> <tr><td>0.130</td><td>12.023</td><td>12.033</td><td>12.029</td></tr> <tr><td>0.143</td><td>11.998</td><td>12.013</td><td>12.011</td></tr> <tr><td>—</td><td>—</td><td>—</td><td>—</td></tr> </tbody> </table>			Load Current [A]	Input Volt. 18.0[V]	Input Volt. 24.0[V]	Input Volt. 36.0[V]	Output Volt. [V]	Output Volt. [V]	Output Volt. [V]	0.000	12.302	12.306	12.315	0.020	12.220	12.212	12.205	0.040	12.179	12.170	12.160	0.060	12.145	12.137	12.126	0.080	12.112	12.107	12.097	0.100	12.078	12.078	12.069	0.120	12.042	12.048	12.042	0.130	12.023	12.033	12.029	0.143	11.998	12.013	12.011	—	—	—	—
Load Current [A]	Input Volt. 18.0[V]	Input Volt. 24.0[V]	Input Volt. 36.0[V]																																															
	Output Volt. [V]	Output Volt. [V]	Output Volt. [V]																																															
0.000	12.302	12.306	12.315																																															
0.020	12.220	12.212	12.205																																															
0.040	12.179	12.170	12.160																																															
0.060	12.145	12.137	12.126																																															
0.080	12.112	12.107	12.097																																															
0.100	12.078	12.078	12.069																																															
0.120	12.042	12.048	12.042																																															
0.130	12.023	12.033	12.029																																															
0.143	11.998	12.013	12.011																																															
—	—	—	—																																															
<b>Object</b> -12V0.13A																																																		
<p>1. Graph</p> <div style="display: flex; justify-content: space-between; align-items: flex-start;"> <div style="width: 45%;"> </div> <div style="width: 45%;"> <p>—△—    Input Volt. 18.0V</p> <p>—□—    Input Volt. 24.0V</p> <p>—○—    Input Volt. 36.0V</p> </div> </div>	<p>2. Values</p> <table border="1" style="width:100%; border-collapse: collapse; text-align: center;"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th>Input Volt. 18.0[V]</th> <th>Input Volt. 24.0[V]</th> <th>Input Volt. 36.0[V]</th> </tr> <tr> <th>Output Volt. [V]</th> <th>Output Volt. [V]</th> <th>Output Volt. [V]</th> </tr> </thead> <tbody> <tr><td>0.000</td><td>-12.289</td><td>-12.292</td><td>-12.302</td></tr> <tr><td>0.020</td><td>-12.205</td><td>-12.196</td><td>-12.189</td></tr> <tr><td>0.040</td><td>-12.163</td><td>-12.153</td><td>-12.143</td></tr> <tr><td>0.060</td><td>-12.129</td><td>-12.120</td><td>-12.109</td></tr> <tr><td>0.080</td><td>-12.095</td><td>-12.089</td><td>-12.079</td></tr> <tr><td>0.100</td><td>-12.061</td><td>-12.060</td><td>-12.051</td></tr> <tr><td>0.120</td><td>-12.025</td><td>-12.030</td><td>-12.024</td></tr> <tr><td>0.130</td><td>-12.006</td><td>-12.015</td><td>-12.011</td></tr> <tr><td>0.143</td><td>-11.979</td><td>-11.994</td><td>-11.993</td></tr> <tr><td>—</td><td>—</td><td>—</td><td>—</td></tr> </tbody> </table>			Load Current [A]	Input Volt. 18.0[V]	Input Volt. 24.0[V]	Input Volt. 36.0[V]	Output Volt. [V]	Output Volt. [V]	Output Volt. [V]	0.000	-12.289	-12.292	-12.302	0.020	-12.205	-12.196	-12.189	0.040	-12.163	-12.153	-12.143	0.060	-12.129	-12.120	-12.109	0.080	-12.095	-12.089	-12.079	0.100	-12.061	-12.060	-12.051	0.120	-12.025	-12.030	-12.024	0.130	-12.006	-12.015	-12.011	0.143	-11.979	-11.994	-11.993	—	—	—	—
Load Current [A]	Input Volt. 18.0[V]	Input Volt. 24.0[V]	Input Volt. 36.0[V]																																															
	Output Volt. [V]	Output Volt. [V]	Output Volt. [V]																																															
0.000	-12.289	-12.292	-12.302																																															
0.020	-12.205	-12.196	-12.189																																															
0.040	-12.163	-12.153	-12.143																																															
0.060	-12.129	-12.120	-12.109																																															
0.080	-12.095	-12.089	-12.079																																															
0.100	-12.061	-12.060	-12.051																																															
0.120	-12.025	-12.030	-12.024																																															
0.130	-12.006	-12.015	-12.011																																															
0.143	-11.979	-11.994	-11.993																																															
—	—	—	—																																															
<p>Note: Slanted line shows the range of the rated load current.          (注)斜線は定格負荷電流範囲を示す。</p>																																																		



Model		ZTW32412	Temperature		25°C																																						
Item		Ripple Voltage (by Load Current) リップル電圧(負荷電流特性)	Testing Circuitry		Figure A																																						
Object		+12V0.13A																																									
1. Graph		<p>-----□----- Input Volt. 18.0V</p> <p>-----△----- Input Volt. 36.0V</p>	2. Values																																								
			<table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th>Input Volt. 18.0 [V]</th> <th>Input Volt. 36.0 [V]</th> </tr> <tr> <th>Ripple Output Volt. [mV]</th> <th>Ripple Output Volt. [mV]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>5</td><td>5</td></tr> <tr><td>0.02</td><td>5</td><td>5</td></tr> <tr><td>0.04</td><td>5</td><td>5</td></tr> <tr><td>0.06</td><td>8</td><td>8</td></tr> <tr><td>0.08</td><td>10</td><td>8</td></tr> <tr><td>0.10</td><td>15</td><td>8</td></tr> <tr><td>0.12</td><td>25</td><td>10</td></tr> <tr><td>0.13</td><td>25</td><td>10</td></tr> <tr><td>0.14</td><td>30</td><td>10</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> </tbody> </table>			Load Current [A]	Input Volt. 18.0 [V]	Input Volt. 36.0 [V]	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]	0.00	5	5	0.02	5	5	0.04	5	5	0.06	8	8	0.08	10	8	0.10	15	8	0.12	25	10	0.13	25	10	0.14	30	10	—	—	—	—	—	—
Load Current [A]	Input Volt. 18.0 [V]	Input Volt. 36.0 [V]																																									
	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]																																									
0.00	5	5																																									
0.02	5	5																																									
0.04	5	5																																									
0.06	8	8																																									
0.08	10	8																																									
0.10	15	8																																									
0.12	25	10																																									
0.13	25	10																																									
0.14	30	10																																									
—	—	—																																									
—	—	—																																									
		<p>Ripple Voltage is shown as p-p in the figure below.</p> <p>Note: Slanted line shows the range of the rated load current.</p> <p>リップル電圧は、下図 p-p 値で示される。 (注)斜線は定格負荷電流範囲を示す。</p> <p>T1: Due to AC Input Line 入力商用周期 T2: Due to Switching スイッチング周期</p>																																									
		<p>Fig. Complex Ripple Wave Form 図 リップル波形詳細図</p>																																									



Model		ZTW32412	Temperature		25°C																																						
Item		Ripple Voltage (by Load Current) リップル電圧(負荷電流特性)	Testing Circuitry		Figure A																																						
Object		-12V0.13A	2. Values																																								
1. Graph		<p>-----□----- Input Volt. 18.0V</p> <p>-----△----- Input Volt. 36.0V</p>	<table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th>Input Volt. 18.0 [V]</th> <th>Input Volt. 36.0 [V]</th> </tr> <tr> <th>Ripple Output Volt. [mV]</th> <th>Ripple Output Volt. [mV]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>5</td><td>5</td></tr> <tr><td>0.02</td><td>5</td><td>5</td></tr> <tr><td>0.04</td><td>8</td><td>5</td></tr> <tr><td>0.06</td><td>10</td><td>5</td></tr> <tr><td>0.08</td><td>15</td><td>5</td></tr> <tr><td>0.10</td><td>20</td><td>5</td></tr> <tr><td>0.12</td><td>25</td><td>5</td></tr> <tr><td>0.13</td><td>30</td><td>8</td></tr> <tr><td>0.14</td><td>35</td><td>8</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> </tbody> </table>			Load Current [A]	Input Volt. 18.0 [V]	Input Volt. 36.0 [V]	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]	0.00	5	5	0.02	5	5	0.04	8	5	0.06	10	5	0.08	15	5	0.10	20	5	0.12	25	5	0.13	30	8	0.14	35	8	—	—	—	—	—	—
Load Current [A]	Input Volt. 18.0 [V]	Input Volt. 36.0 [V]																																									
	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]																																									
0.00	5	5																																									
0.02	5	5																																									
0.04	8	5																																									
0.06	10	5																																									
0.08	15	5																																									
0.10	20	5																																									
0.12	25	5																																									
0.13	30	8																																									
0.14	35	8																																									
—	—	—																																									
—	—	—																																									
<p>Ripple Voltage is shown as p-p in the figure below.</p> <p>Note: Slanted line shows the range of the rated load current.</p> <p>リップル電圧は、下図 p-p 値で示される。</p> <p>(注) 斜線は定格負荷電流範囲を示す。</p>		<p>T1: Due to AC Input Line 入力商用周期</p> <p>T2: Due to Switching スイッチング周期</p>																																									
<p>Fig. Complex Ripple Wave Form</p> <p>図 リップル波形詳細図</p>																																											



Model		ZTW32412	Temperature		25°C																																						
Item		Ripple-Noise リップルノイズ	Testing Circuitry		Figure A																																						
Object		+12V0.13A																																									
1. Graph			2. Values																																								
<p>[mV]</p> <p>-----□----- Input Volt. 18.0V</p> <p>-----△----- Input Volt. 36.0V</p> <p>Ripple-Noise</p> <p>Load Current [A]</p>			<table border="1"> <thead> <tr> <th rowspan="2">Load current [A]</th> <th>Input Volt. 18.0 [V]</th> <th>Input Volt. 36.0 [V]</th> </tr> <tr> <th>Ripple-Noise [mV]</th> <th>Ripple-Noise [mV]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>15</td><td>15</td></tr> <tr><td>0.02</td><td>15</td><td>20</td></tr> <tr><td>0.04</td><td>15</td><td>20</td></tr> <tr><td>0.06</td><td>15</td><td>20</td></tr> <tr><td>0.08</td><td>20</td><td>20</td></tr> <tr><td>0.10</td><td>25</td><td>20</td></tr> <tr><td>0.12</td><td>30</td><td>20</td></tr> <tr><td>0.13</td><td>30</td><td>20</td></tr> <tr><td>0.14</td><td>35</td><td>20</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> </tbody> </table>			Load current [A]	Input Volt. 18.0 [V]	Input Volt. 36.0 [V]	Ripple-Noise [mV]	Ripple-Noise [mV]	0.00	15	15	0.02	15	20	0.04	15	20	0.06	15	20	0.08	20	20	0.10	25	20	0.12	30	20	0.13	30	20	0.14	35	20	—	—	—	—	—	—
Load current [A]	Input Volt. 18.0 [V]	Input Volt. 36.0 [V]																																									
	Ripple-Noise [mV]	Ripple-Noise [mV]																																									
0.00	15	15																																									
0.02	15	20																																									
0.04	15	20																																									
0.06	15	20																																									
0.08	20	20																																									
0.10	25	20																																									
0.12	30	20																																									
0.13	30	20																																									
0.14	35	20																																									
—	—	—																																									
—	—	—																																									
<p>Ripple-Noise is shown as p-p in the figure below.</p> <p>Note: Slanted line shows the range of the rated load current.</p> <p>リップルノイズは、下図 p-p 値で示される。</p> <p>(注) 斜線は定格負荷電流範囲を示す。</p> <p>T1: Due to AC Input Line 入力商用周期</p> <p>T2: Due to Switching スイッチング周期</p> <p>Ripple-Noise [mVp-p]</p>																																											
<p>Fig. Complex Ripple Wave Form</p> <p>図 リップル波形詳細図</p>																																											




Model		ZTW32412	Temperature		25°C																																						
Item		Ripple-Noise リップルノイズ	Testing Circuitry		Figure A																																						
Object		-12V0.13A																																									
<p>1. Graph</p> <p>[mV]</p> <p>-----□----- Input Volt. 18.0V</p> <p>-----△----- Input Volt. 36.0V</p>			<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Load current [A]</th> <th>Input Volt. 18.0 [V]</th> <th>Input Volt. 36.0 [V]</th> </tr> <tr> <th>Ripple-Noise [mV]</th> <th>Ripple-Noise [mV]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>15</td><td>15</td></tr> <tr><td>0.02</td><td>15</td><td>15</td></tr> <tr><td>0.04</td><td>15</td><td>15</td></tr> <tr><td>0.06</td><td>15</td><td>15</td></tr> <tr><td>0.08</td><td>20</td><td>15</td></tr> <tr><td>0.10</td><td>25</td><td>15</td></tr> <tr><td>0.12</td><td>30</td><td>15</td></tr> <tr><td>0.13</td><td>35</td><td>15</td></tr> <tr><td>0.14</td><td>40</td><td>15</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> </tbody> </table>			Load current [A]	Input Volt. 18.0 [V]	Input Volt. 36.0 [V]	Ripple-Noise [mV]	Ripple-Noise [mV]	0.00	15	15	0.02	15	15	0.04	15	15	0.06	15	15	0.08	20	15	0.10	25	15	0.12	30	15	0.13	35	15	0.14	40	15	—	—	—	—	—	—
Load current [A]	Input Volt. 18.0 [V]	Input Volt. 36.0 [V]																																									
	Ripple-Noise [mV]	Ripple-Noise [mV]																																									
0.00	15	15																																									
0.02	15	15																																									
0.04	15	15																																									
0.06	15	15																																									
0.08	20	15																																									
0.10	25	15																																									
0.12	30	15																																									
0.13	35	15																																									
0.14	40	15																																									
—	—	—																																									
—	—	—																																									
<p>Ripple-Noise is shown as p-p in the figure below.                  Note: Slanted line shows the range of the rated load current.</p> <p>リップルノイズは、下図 p-p 値で示される。                  (注)斜線は定格負荷電流範囲を示す。</p> <p>T1: Due to AC Input Line                  入力商用周期</p> <p>T2: Due to Switching                  スイッチング周期</p>																																											
<p>Fig. Complex Ripple Wave Form                  図 リップル波形詳細図</p>																																											



Model	ZTW32412
Item	Overcurrent Protection 過電流保護
Object	+12V0.13A

Temperature 25°C  
Testing Circuitry Figure A

1. Graph




2. Values

Output Voltage [V]	Input Volt. 18.0[V]	Input Volt. 24.0[V]	Input Volt. 36.0[V]
	Load Current [A]	Load Current [A]	Load Current [A]
12.00	0.155	0.169	0.171
11.40	0.262	0.300	0.253
10.80	0.271	0.308	0.256
9.60	0.292	0.323	0.264
8.40	0.308	0.335	0.267
7.20	0.322	0.345	0.269
6.00	0.334	0.348	0.267
4.80	0.339	0.346	0.260
3.60	0.336	0.334	0.249
2.40	0.320	0.309	0.231
1.20	0.295	0.274	0.213
0.00	0.320	0.306	0.260

Object	-12V0.13A
--------	-----------

1. Graph



2. Values

Output Voltage [V]	Input Volt. 18.0[V]	Input Volt. 24.0[V]	Input Volt. 36.0[V]
	Load Current [A]	Load Current [A]	Load Current [A]
-12.00	0.146	0.155	0.157
-11.40	0.266	0.303	0.255
-10.80	0.275	0.310	0.259
-9.60	0.294	0.325	0.266
-8.40	0.311	0.337	0.271
-7.20	0.326	0.347	0.273
-6.00	0.338	0.353	0.271
-4.80	0.343	0.350	0.265
-3.60	0.341	0.339	0.254
-2.40	0.327	0.314	0.237
-1.20	0.301	0.278	0.219
0.00	0.306	0.291	0.246

Note: Slanted line shows the range of the rated load current.

(注)斜線は定格負荷電流範囲を示す。

# COSEL



Model	ZTW32412	Temperature	25°C
Item	Dynamic Load Responce 動的負荷変動	Testing Circuitry	Figure A
Object	+12V0.13A		

Input Volt. 24.0 V  
Cycle 100 mS

Load Current



Min. Load ←→  
Load 100 %

200 mV/div





Min. Load ←→  
Load 50 %

200 mV/div



Load 50%←→  
Load 100 %

200 mV/div



1 mS/div

# COSEL



Model	ZTW32412	Temperature	25°C
Item	Dynamic Load Responce 動的負荷変動	Testing Circuitry	Figure A
Object	-12V0.13A		

Input Volt. 24.0 V  
Cycle 100 mS

Load Current



Min. Load ←→  
Load 100 %

200 mV/div





Min. Load ←→  
Load 50 %

200 mV/div



Load 50% ←→  
Load 100 %

200 mV/div




1 mS/div

# COSEL

Model	ZTW32412	Temperature	25°C
Item	Rise and Fall Time 立上り、立下り時間	Testing Circuitry	Figure A
Object	+12V 0.13A		

1. Graph


Input Volt. 18.0 V



2. Values

[ms]

Load \ Time	T <sub>d</sub>	T <sub>r</sub>	T <sub>s</sub>	T <sub>h</sub>	T <sub>f</sub>
50 %	0.05	1.15	1.20	0.23	1.80
100 %	0.05	1.30	1.35	0.15	0.95




# COSEL

Model	ZTW32412	Temperature	25°C
Item	Rise and Fall Time 立上り、立下り時間	Testing Circuitry	Figure A
Object	-12V 0.13A		


1. Graph

Input Volt. 18.0 V



2. Values


Load	Time	[mS]				
		T <sub>d</sub>	T <sub>r</sub>	T <sub>s</sub>	T <sub>h</sub>	T <sub>f</sub>
50 %		0.05	1.20	1.25	0.23	1.84
100 %		0.05	1.35	1.40	0.16	0.95





Model	ZTW32412	Testing Circuitry Figure A
Item	Ambient Temperature Drift 周囲温度変動	
Object	+12V0.13A	

1. Graph




2. Values

Temperature [°C]	Input Volt. 18.0[V]	Input Volt. 24.0[V]	Input Volt. 36.0[V]
	Output Volt. [V]	Output Volt. [V]	Output Volt. [V]
-30	12.057	12.067	12.063
-20	12.054	12.062	12.058
-10	12.049	12.056	12.052
0	12.044	12.052	12.047
10	12.040	12.047	12.042
25	12.030	12.038	12.033
30	12.027	12.034	12.029
40	12.019	12.028	12.022
55	12.006	12.015	12.010
60	12.001	12.010	12.006
-	-	-	-

Object

-12V0.13A

1. Graph



2. Values

Temperature [°C]	Input Volt. 18.0[V]	Input Volt. 24.0[V]	Input Volt. 36.0[V]
	Output Volt. [V]	Output Volt. [V]	Output Volt. [V]
-30	-12.060	-12.061	-12.053
-20	-12.052	-12.054	-12.047
-10	-12.043	-12.046	-12.039
0	-12.036	-12.040	-12.033
10	-12.028	-12.033	-12.027
25	-12.016	-12.023	-12.016
30	-12.012	-12.018	-12.012
40	-12.003	-12.011	-12.005
55	-11.988	-11.997	-11.992
60	-11.982	-11.992	-11.987
-	-	-	-

Note: Slanted line shows the range of the rated ambient temperature.

(注)斜線は定格周囲温度範囲を示す。




Model	ZTW32412
Item	Minimum Input Voltage for Regulated Output Voltage 最低レギュレーション電圧
Object	+12V0.13A

Testing Circuitry Figure A

1. Graph  
[V]

-----□----- Load 50%  
-----△----- Load 100%




2. Values

Ambient Temp. [°C]	Load 50% Input Volt. [V]	Load 100% Input Volt. [V]
-30	10.5	12.1
-20	10.3	11.7
-10	10.2	11.6
0	10.0	11.2
10	9.8	11.0
25	9.5	10.9
30	9.4	10.7
40	9.3	10.9
55	9.1	10.9
60	9.0	10.9
—	—	—

Object -12V0.13A

[V]

-----□----- Load 50%  
-----△----- Load 100%




2. Values

Ambient Temp. [°C]	Load 50% Input Volt. [V]	Load 100% Input Volt. [V]
-30	10.5	12.1
-20	10.3	11.7
-10	10.2	11.6
0	10.0	11.2
10	9.8	11.0
25	9.5	10.9
30	9.4	10.7
40	9.3	10.9
55	9.1	10.9
60	9.0	10.9
—	—	—

Note: Slanted line shows the range of the rated ambient temperature.


(注)斜線は定格周囲温度範囲を示す。



Testing Circuitry Figure A

2. Values

Ambient Temp. [°C]	Load 50%	Load 100%
	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]
-30	15	80
-20	10	60
-10	10	50
0	5	40
10	5	35
25	5	35
30	5	30
40	5	30
55	5	30
60	5	30
—	—	—



2. Values


Ambient Temp. [°C]	Load 50%	Load 100%
	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]
-30	10	75
-20	10	60
-10	10	50
0	10	40
10	5	35
25	5	30
30	5	30
40	5	30
55	5	30
60	5	35
—	—	—



Model	ZTW32412	Temperature	25 °C
Item	Time Lapse Drift 経時ドリフト	Testing Circuitry	Figure A

Object +12V0.13A

1. Graph




2. Values

Time since start [H]	Output Voltage [V]
0.0	12.050
0.5	12.042
1.0	12.042
2.0	12.042
3.0	12.042
4.0	12.042
5.0	12.042
6.0	12.042
7.0	12.042
8.0	12.042

Object -12V0.13A

1. Graph



2. Values

Time since start [H]	Output Voltage [V]
0.0	-12.028
0.5	-12.018
1.0	-12.018
2.0	-12.018
3.0	-12.018
4.0	-12.018
5.0	-12.018
6.0	-12.018
7.0	-12.018
8.0	-12.018



Model		ZTW32412	Testing Circuitry Figure A
Item	Output Voltage Accuracy 定電圧精度		

**Output Voltage Accuracy**

This is defined as the value of the output voltage, regulation load, ambient temperature and input voltage varied at random in the range as specified below.

- Temperature : -20~55 °C
- Input Voltage : 18.0~36.0 V
- Load Current ( AVR 1 ) : 0.00~0.13 A
- ( AVR 2 ) : 0.00~0.13 A

\* Output Voltage Accuracy =  $\pm (\text{Maximum of Output Voltage} - \text{Minimum of Output Voltage}) / 2$

\* Output Voltage Accuracy (Ration) =  $\frac{\text{Voltage Accuracy}}{\text{Rated Output Voltage}} \times 100$

**定電圧精度**

周囲温度、入力電圧、負荷を下記仕様内で、任意に変動させたときの出力電圧の変動をいう。

- 周囲温度 -20~55 °C
- 入力電圧 18.0~36.0 V
- 負荷電流 (AVR 1) 0.00~0.13 A
- (AVR 2) 0.00~0.13 A

\* 定電圧精度(変動値) =  $\pm (\text{出力電圧の最高値} - \text{出力電圧の最低値}) / 2$

\* 定電圧精度(変動率) =  $\frac{\text{変動値}}{\text{定格出力電圧}} \times 100$

Object +12V0.13A

Item	Temperature [°C]	Input Voltage [V]	Output Current [A]	Output Voltage [V]	Output Voltage Accuracy [mV]	Output Voltage Accuracy(Ration) [%]
Maximum Voltage	-20	24.0	0.13	12.062	±144	±1.2
Minimum Voltage	25	18.0	0.00	11.775		

Object -12V0.13A

Item	Temperature [°C]	Input Voltage [V]	Output Current [A]	Output Voltage [V]	Output Voltage Accuracy [mV]	Output Voltage Accuracy(Ration) [%]
Maximum Voltage	-20	24.0	0.13	-12.054	±147	±1.3
Minimum Voltage	55	18.0	0.00	-11.760		



<b>COSEL</b>		
Model	ZTW32412	
Item	Condensation 結露特性	Testing Circuitry Figure A
Object	+12V0.13A	

1. Condensation test

Testing procedure is as follows.

- ① Keeping and cooling the unit in a tank at -10°C for an hour with the input off.
- ② Taking it out of the tank and dewing itself in a room where the temperature is 25°C and the humidity is 40%RH.
- ③ Testing electrical characteristics of the unit to confirm there be no fault.

1. 結露特性試験

入力を切った状態で、恒温槽で-10°Cに冷却しておき、約1時間後に恒温槽から取り出し、室温25°C、湿度40%RHの状態におき結露させ、その電気的特性の測定を行い、異常のないことを確認する。

2. Values

Item	Data	Testing Conditions
Output Voltage [V]	11.811	Input Volt. : 24V, Load Current:0.13A
Line Regulation [mV]	10	Input Volt. : 18~36V, Load Current:0.13A
Load Regulation [mV]	241	Input Volt. : 24V, Load Current:0~0.13A



<b>COSEL</b>		
Model	ZTW32412	
Item	Condensation 結露特性	Testing Circuitry Figure A
Object	-12V0.13A	

1. Condensation test

Testing procedure is as follows.

- ① Keeping and cooling the unit in a tank at -10°C for an hour with the input off.
- ② Taking it out of the tank and dewing itself in a room where the temperature is 25°C and the humidity is 40%RH.
- ③ Testing electrical characteristics of the unit to confirm there be no fault.

1. 結露特性試験

入力を切った状態で、恒温槽で-10℃に冷却しておき、約1時間後に恒温槽から取り出し、室温25℃、湿度40%RHの状態におき結露させ、その電気的特性の測定を行い、異常のないことを確認する。

2. Values

Item	Data	Testing Conditions
Output Voltage [V]	-11.784	Input Volt. : 24V, Load Current:0.13A
Line Regulation [mV]	13	Input Volt. : 18~36V, Load Current:0.13A
Load Regulation [mV]	296	Input Volt. : 24V, Load Current:0~0.13A

COSEL




Figure A