

COSEL

Model LHP300F-24-Y Item Switching Frequency Object	Temperature 25°C																								
	2. Values																								
<p>1. Graph</p> <p>Input Voltage : 100VAC Output Voltage : 24V</p> <table border="1"> <thead> <tr> <th>Load Current [A]</th> <th>Switching Frequency [kHz]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>86</td></tr> <tr><td>1.25</td><td>83</td></tr> <tr><td>2.50</td><td>83</td></tr> <tr><td>3.75</td><td>80</td></tr> <tr><td>5.00</td><td>82</td></tr> <tr><td>6.25</td><td>80</td></tr> <tr><td>7.50</td><td>79</td></tr> <tr><td>8.75</td><td>79</td></tr> <tr><td>10.00</td><td>77</td></tr> <tr><td>11.25</td><td>77</td></tr> <tr><td>12.50</td><td>75</td></tr> </tbody> </table>		Load Current [A]	Switching Frequency [kHz]	0.00	86	1.25	83	2.50	83	3.75	80	5.00	82	6.25	80	7.50	79	8.75	79	10.00	77	11.25	77	12.50	75
Load Current [A]	Switching Frequency [kHz]																								
0.00	86																								
1.25	83																								
2.50	83																								
3.75	80																								
5.00	82																								
6.25	80																								
7.50	79																								
8.75	79																								
10.00	77																								
11.25	77																								
12.50	75																								
<p>Input Voltage : 230VAC Output Voltage : 24V</p> <table border="1"> <thead> <tr> <th>Load Current [A]</th> <th>Switching Frequency [kHz]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>84</td></tr> <tr><td>1.25</td><td>82</td></tr> <tr><td>2.50</td><td>81</td></tr> <tr><td>3.75</td><td>81</td></tr> <tr><td>5.00</td><td>79</td></tr> <tr><td>6.25</td><td>79</td></tr> <tr><td>7.50</td><td>79</td></tr> <tr><td>8.75</td><td>77</td></tr> <tr><td>10.00</td><td>77</td></tr> <tr><td>11.25</td><td>76</td></tr> <tr><td>12.50</td><td>78</td></tr> </tbody> </table>		Load Current [A]	Switching Frequency [kHz]	0.00	84	1.25	82	2.50	81	3.75	81	5.00	79	6.25	79	7.50	79	8.75	77	10.00	77	11.25	76	12.50	78
Load Current [A]	Switching Frequency [kHz]																								
0.00	84																								
1.25	82																								
2.50	81																								
3.75	81																								
5.00	79																								
6.25	79																								
7.50	79																								
8.75	77																								
10.00	77																								
11.25	76																								
12.50	78																								

Note: Slanted line shows the range of the rated load current.